2.7-V TO 5.5-V 12-BIT 3-μS QUADRUPLE DIGITAL-TO-ANALOG CONVERTERS WITH POWER DOWN

SLAS188B – SEPTEMBER 1998 – REVISED APRIL 2003

- **Four 12-Bit D/A Converters**
- **Programmable Settling Time of Either 3 μs or 9 μs Typ**
- **TMS320, (Q)SPI™, and Microwire™ Compatible Serial Interface**
- **Internal Power-On Reset**
- **Low Power Consumption:**
  8 mW, Slow Mode – 5-V Supply
  3.6 mW, Slow Mode – 3-V Supply
- **Reference Input Buffer**
- **Voltage Output Range . . . 2× the Reference Input Voltage**
- **Monotonic Over Temperature**
- **Dual 2.7-V to 5.5-V Supply (Separate Digital and Analog Supplies)**
- **Hardware Power Down (10 nA)**
- **Software Power Down (10 nA)**
- **Simultaneous Update**

applications

- **Battery Powered Test Instruments**
- **Digital Offset and Gain Adjustment**
- **Industrial Process Controls**
- **Machine and Motion Control Devices**
- **Communications**
- **Arbitrary Waveform Generation**

D OR PW PACKAGE
(TOP VIEW)



description

The TLV5614 is a quadruple 12-bit voltage output digital-to-analog converter (DAC) with a flexible 4-wire serial interface. The 4-wire serial interface allows glueless interface to TMS320, SPI, QSPI, and Microwire serial ports. The TLV5614 is programmed with a 16-bit serial word comprised of a DAC address, individual DAC control bits, and a 12-bit DAC value. The device has provision for two supplies: one digital supply for the serial interface (via pins DV_{DD} and DGND), and one for the DACs, reference buffers, and output buffers (via pins AV_{DD} and AGND). Each supply is independent of the other, and can be any value between 2.7 V and 5.5 V. The dual supplies allow a typical application where the DAC is controlled via a microprocessor operating on a 3 V supply (also used on pins DV_{DD} and DGND), with the DACs operating on a 5 V supply. Of course, the digital and analog supplies can be tied together.

The resistor string output voltage is buffered by a x2 gain rail-to-rail output buffer. The buffer features a Class AB output stage to improve stability and reduce settling time. A rail-to-rail output stage and a power-down mode makes it ideal for single voltage, battery based applications. The settling time of the DAC is programmable to allow the designer to optimize speed versus power dissipation. The settling time is chosen by the control bits within the 16-bit serial input string. A high-impedance buffer is integrated on the REFINAB and REFINCD terminals to reduce the need for a low source impedance drive to the terminal. REFINAB and REFINCD allow DACs A and B to have a different reference voltage then DACs C and D.

The TLV5614 is implemented with a CMOS process and is available in a 16-terminal SOIC package. The TLV5614C is characterized for operation from 0°C to 70°C. The TLV5614I is characterized for operation from –40°C to 85°C.

Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

SPI and QSPI are trademarks of Motorola, Inc.
Microwire is a trademark of National Semiconductor Corporation.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 1998 – 2003, Texas Instruments Incorporated

AVAILABLE OPTIONS

T_A	PACKAGE		
	SOIC (D)	TSSOP (PW)	WSP† (YE)
0°C to 70°C	TLV5614CD	TLV5614CPW	—
–40°C to 85°C	TLV5614ID	TLV5614IPW	TLV5614IYE

† Wafer Scale Packaging, also called Bumped Dice. See Figure 17.

functional block diagram



Terminal Functions

TERMINAL NAME	TERMINAL NO.	I/O	DESCRIPTION
AGND	9		Analog ground
AV_{DD}	16		Analog supply
$\overline{CS}$	6	I	Chip select. This terminal is active low.
DGND	8		Digital ground
DIN	4	I	Serial data input
DV_{DD}	1		Digital supply
FS	7	I	Frame sync input. The falling edge of the frame sync pulse indicates the start of a serial data frame shifted out to the TLV5614.
$\overline{PD}$	2	I	Power down pin. Powers down all DACs (overriding their individual power down settings), and all output stages. This terminal is active low.
$\overline{LDAC}$	3	I	Load DAC. When the $\overline{LDAC}$ signal is high, no DAC output updates occur when the input digital data is read into the serial interface. The DAC outputs are only updated when $\overline{LDAC}$ is low.
REFINAB	15	I	Voltage reference input for DACs A and B.
REFINCD	10	I	Voltage reference input for DACs C and D.
SCLK	5	I	Serial clock input
OUTA	14	O	DACA output
OUTB	13	O	DACB output
OUTC	12	O	DACC output
OUTD	11	O	DACD output

absolute maximum ratings over operating free-air temperature range (unless otherwise noted)†

Supply voltage, (DV_{DD}, AV_{DD} to GND) . . . . . 7 V
Supply voltage difference, (AV_{DD} to DV_{DD}) . . . . . –2.8 V to 2.8 V
Digital input voltage range . . . . . –0.3 V to DV_{DD} + 0.3 V
Reference input voltage range . . . . . –0.3 V to AV_{DD} + 0.3 V
Operating free-air temperature range, T_A: TLV5614C . . . . . 0°C to 70°C
TLV5614I . . . . . –40°C to 85°C
Storage temperature range, T_{stg} . . . . . –65°C to 150°C
Lead temperature 1,6 mm (1/16 inch) from case for 10 seconds . . . . . 260°C

† Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

recommended operating conditions

		MIN	NOM	MAX	UNIT
Supply voltage, AV_{DD}, DV_{DD}	5-V supply	4.5	5	5.5	V
	3-V supply	2.7	3	3.3	
High-level digital input voltage, V_{IH}	DV_{DD} = 2.7 V	2			V
	DV_{DD} = 5.5 V	2.4			
Low-level digital input voltage, V_{IL}	DV_{DD} = 2.7 V			0.6	V
	DV_{DD} = 5.5 V			1	
Reference voltage, V_{ref} to REFINAB, REFINCD terminal	5-V supply, See Note 1	0	2.048	V_{DD}–1.5	V
	3-V supply, See Note 1	0	1.024	V_{DD}–1.5	
Load resistance, R_L		2	10		kΩ
Load capacitance, C_L				100	pF
Serial clock rate, SCLK				20	MHz
Operating free-air temperature	TLV5614C	0		70	°C
	TLV5614I	–40		85	

NOTE 1: Voltages greater than $AV_{DD}/2$ cause output saturation for large DAC codes.

electrical characteristics over recommended operating free-air temperature range, supply voltages, and reference voltages (unless otherwise noted)

static DAC specifications

PARAMETER			TEST CONDITIONS	MIN	TYP	MAX	UNIT
	Resolution			12			bits
	Integral nonlinearity (INL), end point adjusted		See Note 2		±1.5	±4	LSB
	Differential nonlinearity (DNL)		See Note 3		±0.5	±1	LSB
E_{ZS}	Zero scale error (offset error at zero scale)		See Note 4			±12	mV
	Zero scale error temperature coefficient		See Note 5		10		ppm/°C
E_G	Gain error		See Note 6			±0.6	% of FS voltage
	Gain error temperature coefficient		See Note 7		10		ppm/°C
PSRR	Power supply rejection ratio	Zero scale	See Notes 8 and 9		–80		dB
		Full scale			–80		dB

NOTES:
2. The relative accuracy or integral nonlinearity (INL) sometimes referred to as linearity error, is the maximum deviation of the output from the line between zero and full scale excluding the effects of zero code and full-scale errors.
3. The differential nonlinearity (DNL) sometimes referred to as differential error, is the difference between the measured and ideal 1 LSB amplitude change of any two adjacent codes. Monotonic means the output voltage changes in the same direction (or remains constant) as a change in the digital input code.
4. Zero-scale error is the deviation from zero voltage output when the digital input code is zero.
5. Zero-scale-error temperature coefficient is given by: E_{ZS} TC = $[E_{ZS}(T_{max}) - E_{ZS}(T_{min})]/V_{ref} \times 10^6/(T_{max} - T_{min})$.
6. Gain error is the deviation from the ideal output ($2\,V_{ref} - 1$ LSB) with an output load of 10 kΩ excluding the effects of the zero-error.
7. Gain temperature coefficient is given by: E_G TC = $[E_G(T_{max}) - E_G(T_{min})]/V_{ref} \times 10^6/(T_{max} - T_{min})$.
8. Zero-scale-error rejection ratio (EZS–RR) is measured by varying the AV_{DD} from 5 ± 0.5 V and 3 ± 0.3 V dc, and measuring the proportion of this signal imposed on the zero-code output voltage.
9. Full-scale rejection ratio (EG-RR) is measured by varying the AV_{DD} from 5 ± 0.5 V and 3 ± 0.3 V dc and measuring the proportion of this signal imposed on the full-scale output voltage after subtracting the zero scale change.

electrical characteristics over recommended operating free-air temperature range, supply voltages, and reference voltages (unless otherwise noted) (continued)

individual DAC output specifications

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
V_O	Voltage output range	R_L = 10 kΩ	0		AV_{DD}–0.4	V
	Output load regulation accuracy	R_L = 2 kΩ vs 10 kΩ		0.1	0.25	% of FS voltage

reference inputs (REFINAB, REFINCD)

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
V_I	Input voltage range	See Note 10		0		AV_{DD}–1.5	V
R_I	Input resistance				10		MΩ
C_I	Input capacitance				5		pF
	Reference feed through	REFIN = 1 V_{pp} at 1 kHz + 1.024 V dc (see Note 11)			–75		dB
	Reference input bandwidth	REFIN = 0.2 V_{pp} + 1.024 V dc large signal	Slow		0.5		MHz
			Fast		1		

NOTES: 10. Reference input voltages greater than V_{DD}/2 cause output saturation for large DAC codes.
11. Reference feedthrough is measured at the DAC output with an input code = 000 hex and a V_{ref} (REFINAB or REFINCD) input = 1.024 Vdc + 1 V_{pp} at 1 kHz.

digital inputs (DIN, $\overline{CS}$, $\overline{LDAC}$, $\overline{PD}$)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
I_{IH}	High-level digital input current	$V_I = V_{DD}$			±1	μA
I_{IL}	Low-level digital input current	V_I = 0 V			±1	μA
C_I	Input capacitance			3		pF

power supply

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
I_{DD}	Power supply current	5-V supply, No load, Clock running, All inputs 0 V or V_{DD}	Slow		1.6	2.4	mA
			Fast		3.8	5.6	
		3-V supply, No load, Clock running, All inputs 0 V or DV_{DD}	Slow		1.2	1.8	mA
			Fast		3.2	4.8	
	Power down supply current (see Figure 12)				10		nA

electrical characteristics over recommended operating free-air temperature range, supply voltages, and reference voltages (unless otherwise noted) (continued)

analog output dynamic performance

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
SR	Output slew rate	C_L = 100 pF, R_L = 10 kΩ, V_O = 10% to 90%, V_{ref} = 2.048 V, 1024 V	Fast		5		V/μs
			Slow		1		V/μs
t_s	Output settling time	To ± 0.5 LSB, C_L = 100 pF, R_L = 10 kΩ, See Notes 12 and 14	Fast		3	5.5	μs
			Slow		9	20	
$t_{s(c)}$	Output settling time, code to code	To ± 0.5 LSB, C_L = 100 pF, R_L = 10 kΩ, See Note 13	Fast		1		μs
			Slow		2		
	Glitch energy	Code transition from 7FF to 800			10		nV-sec
SNR	Signal-to-noise ratio	Sinewave generated by DAC, Reference voltage = 1.024 at 3 V and 2.048 at 5 V, f_S = 400 KSPS, f_{OUT} = 1.1 kHz sinewave, C_L = 100 pF, R_L = 10 kΩ, BW = 20 kHz			74		dB
S/(N+D)	Signal to noise + distortion				66		
THD	Total harmonic distortion				–68		
SFDR	Spurious free dynamic range				70		

NOTES: 12. Settling time is the time for the output signal to remain within ±0.5 LSB of the final measured value for a digital input code change ofFFF hex to 080 hex for 080 hex to FFF hex.
13. Settling time is the time for the output signal to remain within ±0.5 LSB of the final measured value for a digital input code change of one count.
14. Limits are ensured by design and characterization, but are not production tested.

electrical characteristics over recommended operating free-air temperature range, supply voltages, and reference voltages (unless otherwise noted) (continued)

digital input timing requirements

		MIN	NOM	MAX	UNIT
$t_{su(CS–FS)}$	Setup time, $\overline{CS}$ low before FS↓	10			ns
$t_{su(FS–CK)}$	Setup time, FS low before first negative SCLK edge	8			ns
$t_{su(C16–FS)}$	Setup time, sixteenth negative SCLK edge after FS low on which bit D0 is sampled before rising edge of FS	10			ns
$t_{su(C16–CS)}$	Setup time. The first positive SCLK edge after D0 is sampled before $\overline{CS}$ rising edge. If FS is used instead of the SCLK positive edge to update the DAC, then the setup time is between the FS rising edge and $\overline{CS}$ rising edge.	10			ns
t_{wH}	Pulse duration, SCLK high	25			ns
t_{wL}	Pulse duration, SCLK low	25			ns
$t_{su(D)}$	Setup time, data ready before SCLK falling edge	8			ns
$t_{h(D)}$	Hold time, data held valid after SCLK falling edge	5			ns
$t_{wH(FS)}$	Pulse duration, FS high	20			ns

PARAMETER MEASUREMENT INFORMATION



Figure 1. Timing Diagram

TYPICAL CHARACTERISTICS

LOAD REGULATION



Figure 2

LOAD REGULATION



Figure 3

LOAD REGULATION



Figure 4

LOAD REGULATION



Figure 5

TYPICAL CHARACTERISTICS

SUPPLY CURRENT vs TEMPERATURE



Figure 6

SUPPLY CURRENT vs TEMPERATURE



Figure 7

TOTAL HARMONIC DISTORTION vs FREQUENCY



Figure 8

TOTAL HARMONIC DISTORTION vs FREQUENCY



Figure 9

TYPICAL CHARACTERISTICS

TOTAL HARMONIC DISTORTION AND NOISE vs FREQUENCY



Figure 10

TOTAL HARMONIC DISTORTION AND NOISE vs FREQUENCY



Figure 11

SUPPLY CURRENT vs TIME (WHEN ENTERING POWER-DOWN MODE)



Figure 12

TYPICAL CHARACTERISTICS



Figure 13



Figure 14

APPLICATION INFORMATION

general function

The TLV5614 is a 12-bit single supply DAC based on a resistor string architecture. The device consists of a serial interface, speed and power down control logic, a reference input buffer, a resistor string, and a rail-to-rail output buffer.

The output voltage (full scale determined by external reference) is given by:

$$2\ \mathrm{REF}\ \frac{\mathrm{CODE}}{2^n}\ [\mathrm{V}]$$

where REF is the reference voltage and CODE is the digital input value within the range of 0_{10} to 2^n–1, where n=12 (bits). The 16-bit data word, consisting of control bits and the new DAC value, is illustrated in the *data format* section. A power-on reset initially resets the internal latches to a defined state (all bits zero).

serial interface

Explanation of data transfer: First, the device has to be enabled with $\overline{CS}$ set to low. Then, a falling edge of FS starts shifting the data bit-per-bit (starting with the MSB) to the internal register on the falling edges of SCLK. After 16 bits have been transferred or FS rises, the content of the shift register is moved to the DAC latch which updates the voltage output to the new level.

The serial interface of the TLV5614 can be used in two basic modes:

- Four wire (with chip select)
- Three wire (without chip select)

Using chip select (four wire mode), it is possible to have more than one device connected to the serial port of the data source (DSP or microcontroller). The interface is compatible with the TMS320™ DSP family. Figure 15 shows an example with two TLV5614s connected directly to a TMS320 DSP.



Figure 15. TMS320 Interface

TMS320 is a trademark of Texas Instruments.

APPLICATION INFORMATION

serial interface (continued)

If there is no need to have more than one device on the serial bus, then $\overline{CS}$ can be tied low. Figure 16 shows an example of how to connect the TLV5614 to a TMS320, SPI, or Microwire port using only three pins.



Figure 16. Three-Wire Interface

Notes on SPI and Microwire: Before the controller starts the data transfer, the software has to generate a falling edge on the I/O pin connected to FS. If the word width is 8 bits (SPI and Microwire), two write operations must be performed to program the TLV5614. After the write operation(s), the DAC output is updated automatically on the next positive clock edge following the sixteenth falling clock edge.

serial clock frequency and update rate

The maximum serial clock frequency is given by:

$$f_{SCLKmax} = \frac{1}{t_{wH(min)} + t_{wL(min)}} = 20\ \text{MHz}$$

The maximum update rate is:

$$f_{UPDATEmax} = \frac{1}{16\left(t_{wH(min)} + t_{wL(min)}\right)} = 1.25\ \text{MHz}$$

Note that the maximum update rate is a theoretical value for the serial interface since the settling time of the TLV5614 has to be considered also.

data format

The 16-bit data word for the TLV5614 consists of two parts:

- Control bits (D15 . . . D12)
- New DAC value (D11 . . . D0)

D15	D14	D13	D12	D11	D10	D9	D8	D7	D6	D5	D4	D3	D2	D1	D0
A1	A0	PWR	SPD	New DAC value (12 bits)											

X: don't care
SPD: Speed control bit. 1 → fast mode 0 → slow mode
PWR: Power control bit. 1 → power down 0 → normal operation

APPLICATION INFORMATION

In power-down mode, all amplifiers within the TLV5614 are disabled. A particular DAC (A, B, C, D) of the TLV5614 is selected by A1 and A0 within the input word.

A1	A0	DAC
0	0	A
0	1	B
1	0	C
1	1	D

Using TLV5614IYE, Bumped Dice

- Melting point of eutectic solder is 183°C.
- Recommended peak reflow temperatures are in the 220°C to 230°C range.
- The use of underfill is required. The use of underfill greatly reduces the risk of thermal mismatch fails.

Underfill is an epoxy/adhesive that may be added during the board assembly process to improve board level/system level reliability. The process is to dispense the epoxy under the dice after die attach reflow. The epoxy adheres to the body of the device and to the printed-circuit board. It reduces stress placed upon the solder joints due to the thermal coefficient of expansion (TCE) mismatch between the board and the component. Underfill material is highly filled with silica or other fillers to increase an epoxy's modulus, reduce creep sensitivity, and decrease the material's TCE.

The recommendation for peak flow temperatures of 220°C to 230°C is based on general empirical results that indicate that this temperature range is needed to facilitate good wetting of the solder bump to the substrate or circuit board pad. Lower peak temperatures may cause nonwets (cold solder joints).



NOTE A: All linear dimensions are in millimeters.
NOTE B: This drawing is subject to change without notice.
NOTE C: Scale = 18x

Figure 17. TLV5614IYE Bumped Dice

TLV5614 interfaced to TMS320C203 DSP

hardware interfacing

Figure 17 shows an example of how to connect the TLV5614 to a TMS320C203 DSP. The serial port is configured in burst mode, with FSX generated by the TMS320C203 to provide the frame sync (FS) input to the TLV5614. Data is transmitted on the DX line, with the serial clock input on the CLKX line. The general-purpose input/output port bits IO0 and IO1 are used to generate the chip select ($\overline{CS}$) and DAC latch update ($\overline{LDAC}$) inputs to the TLV5614. The active low power down ($\overline{PD}$) is pulled high all the time to ensure the DACs are enabled.



Figure 18. TLV5614 Interfaced With TMS320C203

software

The application example outputs a differential in-phase (sine) signal between the VOUTA and VOUTB pins, and its quadrature (cosine) signal as the differential signal between VOUTC and VOUTD.

The on-chip timer is used to generate interrupts at a fixed frequency. The related interrupt service routine pulses $\overline{LDAC}$ low to update all 4 DACs simultaneously, then fetches and writes the next sample to all 4 DACs. The samples are stored in a look-up table, which describes two full periods of a sine wave.

The synchronous serial port of the DSP is used in burst mode. In this mode, the processor generates an FS pulse preceding the MSB of every data word. If multiple, contiguous words are transmitted, a violation of the tsu(C16–FS) timing requirement occurs. To avoid this, the program waits until the transmission of the previous word has been completed.

APPLICATION INFORMATION

```
;-------------------------------------------------------------------------------
; Processor:  TMS320C203 runnning at 40 MHz
;
; Description:
;
; This program generates a differential in-phase (sine) on (OUTA-OUTB) and it's
; quadrature (cosine) as a differential signal on (OUTC-OUTD).
;
; The DAC codes for the signal samples are stored as a table of 64 12-bit values,
; describing 2 periods of a sine function. A rolling pointer is used to address the
; table location in the first period of this waveform, from which the DAC A samples
; are read. The samples for the other 3 DACs are read at an offset to this rolling
; pointer:
;  DAC    Function     Offset from rolling pointer
;   A     sine         0
;   B     inverse sine 16
;   C     cosine       8
;   D     inverse cosine24
;
; The on-chip timer is used to generate interrupts at a fixed rate. The interrupt
; service routine first pulses LDAC low to update all DACs simultaneously
; with the values which were written to them in the previous interrupt. Then all
; 4 DAC values are fetched and written out through the synchronous serial interface
; Finally, the rolling pointer is incremented to address the next sample, ready for
; the next interrupt.
;
; © 1998, Texas Instruments Inc.
;-------------------------------------------------------------------------------
;------------------------------ I/O and memory mapped regs -----------------------------
      .include "regs.asm"
;-------jump vectors ------------------------------------------------------------------
      .ps   0h
      b     start
      b     int1
      b     int23
      b     timer_isr;
---------- variables ---------------------------------------------------------
temp         .equ   0060h
r_ptr        .equ   0061h
iosr_stat    .equ   0062h
DACa_ptr     .equ   0063h
DACb_ptr     .equ   0064h
DACc_ptr     .equ   0065h
DACd_ptr     .equ   0066h
;----------constants---------------------------------------------------------------
; DAC control bits to be OR'ed onto data
; all fast mode
DACa_control .equ   01000h
DACb_control .equ   05000h
DACc_control .equ   09000h
DACd_control .equ   0d000h
;---------- tables --------------------------------
   .ds    02000h
sinevals
   .word  00800h
   .word  0097Ch
   .word  00AE9h
   .word  00C3Ah
   .word  00D61h
   .word  00E53h
   .word  00F07h
   .word  00F76h
   .word  00F9Ch
   .word  00F76h
   .word  00F07h
   .word  00E53h
```

APPLICATION INFORMATION

```
.word  00D61h
.word  00C3Ah
.word  00AE9h
.word  0097Ch
.word  00800h
.word  00684h
.word  00517h
.word  003C6h
.word  0029Fh
.word  001ADh
.word  000F9h
.word  0008Ah
.word  00064h
.word  0008Ah
.word  000F9h
.word  001ADh
.word  0029Fh
.word  003C6h
.word  00517h
.word  00684h
.word  00800h
.word  0097Ch
.word  00AE9h
.word  00C3Ah
.word  00D61h
.word  00E53h
.word  00F07h
.word  00F76h
.word  00F9Ch
.word  00F76h
.word  00F07h
.word  00E53h
.word  00D61h
.word  00C3Ah
.word  00AE9h
.word  0097Ch
.word  00800h
.word  00684h
.word  00517h
.word  003C6h
.word  0029Fh
.word  001ADh
.word  000F9h
.word  0008Ah
.word  00064h
.word  0008Ah
.word  000F9h
.word  001ADh
.word  0029Fh
.word  003C6h
.word  00517h
.word  00684h
```

APPLICATION INFORMATION

```
;-------------------------------------------------------------------------------
; Main Program
;-------------------------------------------------------------------------------
      .ps    1000h
      .entry
start
;-------------------------------------------------------------------------------
; disable interrupts
;-------------------------------------------------------------------------------
      setc   INTM      ; disable maskable interrupts
      splk   #0ffffh, IFR; clear all interrupts
      splk   #0004h, IMR; timer interrupts unmasked
;-------------------------------------------------------------------------------
; set up the timer
; timer period set by values in PRD and TDDR
; period = (CLKOUT1 period) x (1+PRD) x (1+TDDR)
; examples for TMS320C203 with 40MHz main clock
; Timer rate     TDDR   PRD
;  80 kHz         9     24 (18h)
;  50 kHz         9     39 (27h)
;-------------------------------------------------------------------------------
prd_val.equ      0018h
tcr_val.equ      0029h
      splk   #0000h, temp; clear timer
      out    temp, TIM
      splk   #prd_val, temp; set PRD
      out    temp, PRD
      splk   #tcr_val, temp; set TDDR, and TRB=1 for auto–reload
      out    temp, TCR
;-------------------------------------------------------------------------------
; Configure IO0/1 as outputs to be :
; IO0  CS  – and set high
; IO1  LDAC   – and set high
;-------------------------------------------------------------------------------
      in     temp, ASPCR; configure as output
      lacl   temp
      or     #0003h
      sacl   temp
      out    temp, ASPCR
      in     temp, IOSR; set them high
      lacl   temp
      or     #0003h
      sacl   temp
      out    temp, IOSR
;-------------------------------------------------------------------------------
; set up serial port for
; SSPCR.TXM=1    Transmit mode – generate FSX
; SSPCR.MCM=1    Clock mode – internal clock source
; SSPCR.FSM=1    Burst mode
;-------------------------------------------------------------------------------
      splk   #0000Eh, temp
      out    temp, SSPCR; reset transmitter
      splk   #0002Eh, temp
      out    temp,SSPCR
;-------------------------------------------------------------------------------
; reset the rolling pointer
;-------------------------------------------------------------------------------
      lacl   #000h
      sacl   r_ptr
;-------------------------------------------------------------------------------
; enable interrupts
;-------------------------------------------------------------------------------
      clrc   INTM      ; enable maskable interrupts
;-------------------------------------------------------------------------------
; loop forever!
;-------------------------------------------------------------------------------
```

APPLICATION INFORMATION

```
next   idle            ;wait for interrupt
       b     next
;-------------------------------------------------------------------------------------
; all else fails stop here
;-------------------------------------------------------------------------------------
done   b     done      ;hang there
;-------------------------------------------------------------------------------------
; Interrupt Service Routines
;-------------------------------------------------------------------------------------
int1   ret       ; do nothing and return
int23  ret       ; do nothing and return
timer_isr:
   in    iosr_stat, IOSR; store IOSR value into variable space
   lacl  iosr_stat    ; load acc with iosr status
   and   #0FFFDh      ; reset IO1 – LDAC low
   sacl  temp         ;
   out   temp, IOSR   ;
   or    #0002h       ; set IO1 – LDAC high
   sacl  temp         ;
   out   temp, IOSR   ;
   and   #0FFFEh      ; reset IO0 – CS low
   sacl  temp         ;
   out   temp, IOSR   ;
   lacl  r_ptr        ; load rolling pointer to accumulator
   add   #sinevals    ; add pointer to table start
   sacl  DACa_ptr     ; to get a pointer for next DAC a sample
   add   #08h         ; add 8 to get to DAC C pointer
   sacl  DACc_ptr
   add   #08h         ; add 8 to get to DAC B pointer
   sacl  DACb_ptr
   add   #08h         ; add 8 to get to DAC D pointer
   sacl  DACd_ptr
   mar   *,ar0        ; set ar0 as current AR

   ; DAC A
   lar   ar0, DACa_ptr; ar0 points to DAC a sample
   lacl  *            ; get DAC a sample into accumulator
   or    #DACa_control; OR in DAC A control bits
   sacl  temp         ;
   out   temp, SDTR   ; send data
;-------------------------------------------------------------------------------------
; We must wait for transmission to complete before writing next word to the SDTR.;
TLV5614/04 interface does not allow the use of burst mode with the full packet; rate, as
we need a CLKX –ve edge to clock in last bit before FS goes high again,; to allow SPI
compatibility.
;-------------------------------------------------------------------------------------
   rpt   #016h        ; wait long enough for this configuration
   nop                ; of MCLK/CLKOUT1 rate

   ; DAC B
   lar   ar0, dacb_ptr; ar0 points to DAC a sample
   lacl  *            ; get DAC a sample into accumulator
   or    #DACb_control; OR in DAC B control bits
   sacl  temp         ;
   out   temp, SDTR   ; send data
   rpt   #016h        ; wait long enough for this configuration
   nop                ; of MCLK/CLKOUT1 rate

; DAC C
   lar   ar0, dacc_ptr; ar0 points to dac a sample
   lacl  *            ; get DAC a sample into accumulator
   or    #DACc_control; OR in DAC C control bits
   sacl     temp      ;
   out      temp, SDTR; send data
   rpt      #016h     ; wait long enough for this configuration
   nop                ; of MCLK/CLKOUT1 rate
```

APPLICATION INFORMATION

```
; DAC D
   lar       ar0, dacd_ptr; ar0 points to DAC a sample
   lacl  *             ; get DAC a sample into accumulator
   or    #dacd_control; OR in DAC D control bits
   sacl  temp          ;
   out   temp, SDTR    ; send data

   lacl  r_ptr         ; load rolling pointer to accumulator
   add   #1h           ; increment rolling pointer
   and   #001Fh        ; count 0–31 then wrap back round
   sacl  r_ptr         ; store rolling pointer
   rpt   #016h         ; wait long enough for this configuration
   nop                 ; of MCLK/CLKOUT1 rate

; now take CS high again
   lacl  iosr_stat     ; load acc with iosr status
   or    #0001h        ; set IO0 – CS high
   sacl  temp          ;
   out   temp, IOSR    ;
   clrc  intm          ; re-enable interrupts
   ret                 ; return from interrupt
.end
```

APPLICATION INFORMATION

TLV5614 interfaced to MCS®51 microcontroller

hardware interfacing

Figure 18 shows an example of how to connect the TLV5614 to an MCS®51 Microcontroller. The serial DAC input data and external control signals are sent via I/O Port 3 of the controller. The serial data is sent on the RxD line, with the serial clock output on the TxD line. Port 3 bits 3, 4, and 5 are configured as outputs to provide the DAC latch update ($\overline{\text{LDAC}}$), chip select ($\overline{\text{CS}}$) and frame sync (FS) signals for the TLV5614. The active low power down pin ($\overline{\text{PD}}$) of the TLV5614 is pulled high to ensure that the DACs are enabled.



Figure 19. TLV5614 Interfaced With MCS®51

software

The example is the same as for the TMS320C203 in this data sheet, but adapted for a MCS®51 controller. It generates a differential in-phase (sine) signal between the VOUTA and VOUTB pins, and its quadrature (cosine) signal is the differential signal between VOUTC and VOUTD.

The on-chip timer is used to generate interrupts at a fixed frequency. The related interrupt service routine pulses $\overline{\text{LDAC}}$ low to update all 4 DACs simultaneously, then fetches and writes the next sample to all 4 DACs. The samples are stored as a look-up table, which describes one full period of a sine wave.

The serial port of the controller is used in Mode 0, which transmits 8 bits of data on RxD, accompanied by a synchronous clock on TxD. Two writes concatenated together are required to write a complete word to the TLV5614. The $\overline{\text{CS}}$ and FS signals are provided in the required fashion through control of IO port 3, which has bit addressable outputs.

APPLICATION INFORMATION

```
;-------------------------------------------------------------------------------
; Processor:  80C51
;
; Description:
;
; This program generates a differential in-phase
(sine) on (OUTA–OUTB) ; and it's quadrature (cosine)
 as a differential signal on (OUTC–OUTD).
;
; © 1998, Texas Instruments Inc.
;-------------------------------------------------------------------------------
NAME   GENIQ
MAIN   SEGMENT      CODE
ISR    SEGMENT      CODE
SINTBL SEGMENT      CODE
VAR1   SEGMENT      DATA
STACK  SEGMENT      IDATA
;-------------------------------------------------------------------------------
; Code start at address 0, jump to start
;-------------------------------------------------------------------------------
   CSEG  AT   0
   LJMP   start        ; Execution starts at address 0 on power–up.
;-------------------------------------------------------------------------------
; Code in the timer0 interrupt vector
;-------------------------------------------------------------------------------
   CSEG  AT   0BH
   LJMP   timer0isr    ; Jump vector for timer 0 interrupt is 000Bh
;-------------------------------------------------------------------------------
; Global variables need space allocated
;-------------------------------------------------------------------------------
   RSEG      VAR1
temp_ptr:    DS     1
rolling_ptr: DS     1
;-------------------------------------------------------------------------------;
Interrupt service routine for timer 0 interrupts
;-------------------------------------------------------------------------------
   RSEG      ISR
timer0isr:
   PUSH      PSW
   PUSH      ACC
   CLR       INT1      ; pulse LDAC low
   SETB      INT1      ; to latch all 4 previous values at the same time
                       ; 1st thing done in timer isr => fixed period
   CLR    T0           ; set CS low

   ; The signal to be output on each DAC is a sine function.
   ; One cycle of a sine wave is held in a table @ sinevals
   ; as 32 samples of msb, lsb pairs (64 bytes).
   ; We have ; one pointer which rolls round this table, rolling_ptr,
   ; incrementing by 2 bytes (1 sample) on each interrupt (at the end of
   ; this routine).

   ; The DAC samples are read at an offset to this rolling pointer:
   ; DAC  Function  Offset from rolling_ptr
   ;  A   sine         0
   ;  B   inverse sine 32
   ;  C   cosine       16
   ;  D   inverse cosine48
   MOV    DPTR,#sinevals; set DPTR to the start of the table
                       ; of sine signal values
   MOV    R7,rolling_ptr; R7 holds the pointer
                       ;into the sine table

   MOV    A,R7         ; get DAC A msb
   MOVC   A,@A+DPTR    ; msb of DAC A is in the ACC
```

APPLICATION INFORMATION

```
    CLR    T1           ; transmit it – set FS low
    MOV    SBUF,A       ; send it out the serial port

    INC    R7           ; increment the pointer in R7
    MOV    A,R7         ; to get the next byte from the table
    MOVC   A,@A+DPTR    ; which is the lsb of this sample, now in ACC
    A_MSB_TX:
    JNB    TI,A_MSB_TX  ; wait for transmit to complete
    CLR    TI           ; clear for new transmit
    MOV    SBUF,A       ; and send out the lsb of DAC A

    ; DAC C next
    ; DAC C codes should be taken from 16 bytes (8 samples) further on
    ; in the sine table – this gives a cosine function
    MOV    A,R7         ; pointer in R7
    ADD    A,#0FH       ; add 15 – already done one INC
    ANL       A,#03FH   ; wrap back round to 0 if > 64
    MOV    R7,A         ; pointer back in R7

    MOVC   A,@A+DPTR    ; get DAC C msb from the table
    ORL    A,#01H       ; set control bits to DAC C address
A_LSB_TX:
    JNB    TI,A_LSB_TX  ; wait for DAC A lsb transmit to complete
    SETB   T1           ; toggle FS
    CLR T1
    CLR    TI           ; clear for new transmit
    MOV    SBUF,A       ; and send out the msb of DAC C
    INC    R7           ; increment the pointer in R7
    MOV    A,R7         ; to get the next byte from the table
    MOVC   A,@A+DPTR    ; which is the lsb of this sample, now in ACC
C_MSB_TX:
    JNB    TI,C_MSB_TX  ; wait for transmit to complete
    CLR    TI           ; clear for new transmit
    MOV    SBUF,A       ; and send out the lsb of DAC C

    ; DAC B next
    ; DAC B codes should be taken from 16 bytes (8 samples) further on
    ; in the sine table – this gives an inverted sine function
    MOV    A,R7         ; pointer in R7
    ADD       A,#0FH    ; add 15 – already done one INC
    ANL    A,#03FH      ; wrap back round to 0 if > 64
    MOV    R7,A         ; pointer back in R7

    MOVC   A,@A+DPTR    ; get DAC B msb from the table
    ORL       A,#02H    ; set control bits to DAC B address

C_LSB_TX:
    JNB    TI,C_LSB_TX  ; wait for DAC C lsb transmit to complete
    SETB   T1           ; toggle FS
    CLR    T1
    CLR    TI           ; clear for new transmit
    MOV    SBUF,A       ; and send out the msb of DAC B

    ; get DAC B LSB
    INC    R7           ; increment the pointer in R7
    MOV    A,R7         ; to get the next byte from the table
    MOVC   A,@A+DPTR    ; which is the lsb of this sample, now in ACC

B_MSB_TX:
    JNB    TI,B_MSB_TX  ; wait for transmit to complete
    CLR    TI           ; clear for new transmit
    MOV       SBUF,A    ; and send out the lsb of DAC B

    ; DAC D next
    ; DAC D codes should be taken from 16 bytes (8 samples) further on
    ; in the sine table – this gives an inverted cosine function
```

APPLICATION INFORMATION

```
    MOV    A,R7          ; pointer in R7
    ADD    A,#0FH        ; add 15 – already done one INC
    ANL       A,#03FH    ; wrap back round to 0 if > 64
    MOV    R7,A          ; pointer back in R7
    MOVC   A,@A+DPTR     ; get DAC D msb from the table
    ORL    A,#03H        ; set control bits to DAC D address

B_LSB_TX:
    JNB    TI,B_LSB_TX   ; wait for DAC B lsb transmit to complete
    SETB   T1            ; toggle FS
    CLR    T1
    CLR    TI  ; clear for new transmit
MOV    SBUF,A            ; and send out the msb of DAC D

    INC    R7            ; increment the pointer in R7
    MOV    A,R7          ; to get the next byte from the table
    MOVC   A,@A+DPTR     ; which is the lsb of this sample, now in ACC
D_MSB_TX:
    JNB    TI,D_MSB_TX   ; wait for transmit to complete
    CLR    TI            ; clear for new transmit
    MOV    SBUF,A        ; and send out the lsb of DAC D

    ; increment the rolling pointer to point to the next sample
    ; ready for the next interrupt
    MOV    A,rolling_ptr
    ADD    A,#02H        ; add 2 to the rolling pointer
    ANL    A,#03FH       ; wrap back round to 0 if > 64
    MOV    rolling_ptr,A ; store in memory again
D_LSB_TX:
    JNB    TI,D_LSB_TX   ; wait for DAC D lsb transmit to complete
    CLR    TI            ; clear for next transmit
    SETB   T1            ; FS high
    SETB   T0            ; CS high
    POP    ACC
    POP    PSW
    RETI

;-------------------------------------------------------------------------------
; Stack needs definition
;-------------------------------------------------------------------------------
    RSEG  STACK
    DS    10h            ; 16 Byte Stack!
;-------------------------------------------------------------------------------
; Main program code
;-------------------------------------------------------------------------------
    RSEG   MAIN
start:
    MOV    SP,#STACK–1   ; first set Stack Pointer
    CLR A
    MOV    SCON,A        ; set serial port 0 to mode 0
    MOV    TMOD,#02H     ; set timer 0 to mode 2 – auto–reload
    MOV    TH0,#038H     ; set TH0 for 5kHs interrupts
    SETB   INT1          ; set LDAC = 1
    SETB   T1            ; set FS = 1
    SETB   T0            ; set CS = 1
    SETB   ET0           ; enable timer 0 interrupts
    SETB   EA            ; enable all interrupts
    MOV    rolling_ptr,A ; set rolling pointer to 0
    SETB   TR0           ; start timer 0
always:
    SJMP   always        ; while(1) !
    RET
;-------------------------------------------------------------------------------
; Table of 32 sine wave samples used as DAC data
;-------------------------------------------------------------------------------
    RSEG   SINTBL
```

APPLICATION INFORMATION

```
sinevals:
   DW     01000H
   DW     0903EH
   DW     05097H
   DW     0305CH
   DW     0B086H
   DW     070CAH
   DW     0F0E0H
   DW     0F06EH
   DW     0F039H
   DW     0F06EH
   DW     0F0E0H
   DW     070CAH
   DW     0B086H
   DW     0305CH
   DW     05097H
   DW     0903EH
   DW     01000H
   DW     06021H
   DW     0A0E8H
   DW     0C063H
   DW     040F9H
   DW     080B5H
   DW     0009FH
   DW     00051H
   DW     00026H
   DW     00051H
   DW     0009FH
   DW     080B5H
   DW     040F9H
   DW     0C063H
   DW     0A0E8H
   DW  06021H
END
```

PACKAGING INFORMATION

Orderable part number	Status (1)	Material type (2)	Package | Pins	Package qty | Carrier	RoHS (3)	Lead finish/ Ball material (4)	MSL rating/ Peak reflow (5)	Op temp (°C)	Part marking (6)
TLV5614CD	Active	Production	SOIC (D) | 16	40 | TUBE	Yes	NIPDAU	Level-1-260C-UNLIM	0 to 70	TLV5614C
TLV5614CD.A	Active	Production	SOIC (D) | 16	40 | TUBE	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	TLV5614C
TLV5614CPW	Active	Production	TSSOP (PW) | 16	90 | TUBE	Yes	NIPDAU	Level-1-260C-UNLIM	0 to 70	TV5614
TLV5614CPW.A	Active	Production	TSSOP (PW) | 16	90 | TUBE	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	TV5614
TLV5614CPWG4	Active	Production	TSSOP (PW) | 16	90 | TUBE	Yes	NIPDAU	Level-1-260C-UNLIM	0 to 70	TV5614
TLV5614CPWR	Active	Production	TSSOP (PW) | 16	2000 | LARGE T&R	Yes	NIPDAU	Level-1-260C-UNLIM	0 to 70	TV5614
TLV5614CPWR.A	Active	Production	TSSOP (PW) | 16	2000 | LARGE T&R	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	TV5614
TLV5614ID	Active	Production	SOIC (D) | 16	40 | TUBE	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	TLV5614I
TLV5614ID.A	Active	Production	SOIC (D) | 16	40 | TUBE	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	TLV5614I
TLV5614IDR	Active	Production	SOIC (D) | 16	2500 | LARGE T&R	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	TLV5614I
TLV5614IDR.A	Active	Production	SOIC (D) | 16	2500 | LARGE T&R	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	TLV5614I
TLV5614IPW	Active	Production	TSSOP (PW) | 16	90 | TUBE	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	TY5614
TLV5614IPW.A	Active	Production	TSSOP (PW) | 16	90 | TUBE	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	TY5614
TLV5614IPWR	Active	Production	TSSOP (PW) | 16	2000 | LARGE T&R	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	TY5614
TLV5614IPWR.A	Active	Production	TSSOP (PW) | 16	2000 | LARGE T&R	Yes	NIPDAU	Level-1-260C-UNLIM	-40 to 85	TY5614

(1) **Status:** For more details on status, see our product life cycle.

(2) **Material type:** When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

(3) **RoHS values:** Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

(4) **Lead finish/Ball material:** Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

(5) **MSL rating/Peak reflow:** The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

(6) **Part marking:** There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

OTHER QUALIFIED VERSIONS OF TLV5614 :

- Enhanced Product : TLV5614-EP

NOTE: Qualified Version Definitions:

- Enhanced Product - Supports Defense, Aerospace and Medical Applications

TAPE AND REEL INFORMATION

REEL DIMENSIONS



TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
TLV5614CPWR	TSSOP	PW	16	2000	330.0	12.4	6.9	5.6	1.6	8.0	12.0	Q1
TLV5614IDR	SOIC	D	16	2500	330.0	16.4	6.5	10.3	2.1	8.0	16.0	Q1
TLV5614IPWR	TSSOP	PW	16	2000	330.0	12.4	6.9	5.6	1.6	8.0	12.0	Q1

TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
TLV5614CPWR	TSSOP	PW	16	2000	350.0	350.0	43.0
TLV5614IDR	SOIC	D	16	2500	350.0	350.0	43.0
TLV5614IPWR	TSSOP	PW	16	2000	350.0	350.0	43.0

TUBE



*All dimensions are nominal

Device	Package Name	Package Type	Pins	SPQ	L (mm)	W (mm)	T (µm)	B (mm)
TLV5614CD	D	SOIC	16	40	505.46	6.76	3810	4
TLV5614CD.A	D	SOIC	16	40	505.46	6.76	3810	4
TLV5614CPW	PW	TSSOP	16	90	530	10.2	3600	3.5
TLV5614CPW.A	PW	TSSOP	16	90	530	10.2	3600	3.5
TLV5614CPWG4	PW	TSSOP	16	90	530	10.2	3600	3.5
TLV5614ID	D	SOIC	16	40	505.46	6.76	3810	4
TLV5614ID.A	D	SOIC	16	40	505.46	6.76	3810	4
TLV5614IPW	PW	TSSOP	16	90	530	10.2	3600	3.5
TLV5614IPW.A	PW	TSSOP	16	90	530	10.2	3600	3.5

D (R–PDSO–G16) PLASTIC SMALL OUTLINE



NOTES:
A. All linear dimensions are in inches (millimeters).
B. This drawing is subject to change without notice.
C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.006 (0,15) each side.
D. Body width does not include interlead flash. Interlead flash shall not exceed 0.017 (0,43) each side.
E. Reference JEDEC MS–012 variation AC.

PACKAGE OUTLINE

PW0016A

TSSOP - 1.2 mm max height

SMALL OUTLINE PACKAGE



NOTES:

1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.15 mm per side.
4. This dimension does not include interlead flash. Interlead flash shall not exceed 0.25 mm per side.
5. Reference JEDEC registration MO-153.



LAND PATTERN EXAMPLE
EXPOSED METAL SHOWN
SCALE: 10X

SOLDER MASK DETAILS

4220204/A 02/2017

NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.
7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.



SOLDER PASTE EXAMPLE
BASED ON 0.125 mm THICK STENCIL
SCALE: 10X

4220204/A 02/2017

NOTES: (continued)

8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
9. Board assembly site may have different recommendations for stencil design.

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES “AS IS” AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI’s products are provided subject to TI’s Terms of Sale or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI’s provision of these resources does not expand or otherwise alter TI’s applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2025, Texas Instruments Incorporated