TPS6273x Programmable Output Voltage Ultra-Low Power Buck Converter With Up to 50 mA / 200 mA Output Current

1 Features

- Industry's Highest Efficiency at Low Output Currents: > 90% With I_{OUT} = 15 µA
- Ultra-Low Power Buck Converter
  - TPS62736 Optimized for 50-mA Output Current
  - TPS62737 Optimized for 200-mA Output Current
  - 1.3-V to 5-V Resistor Programmable Output Voltage Range
  - 2-V to 5.5-V Input Operating Range
  - 380-nA and 375-nA Quiescent Current During Active Operation for TPS62736 and TPS62737
  - 10-nA Quiescent Current During Ship Mode Operation
  - 2% Voltage Regulation Accuracy
- 100% Duty Cycle (Pass Mode)
- EN1 and EN2 Control
  - Two Power-Off States:
    1. Shipmode (Full Power-Off State)
    2. Standby Mode Includes VIN_OK Indication
- Input Power-Good Indication (VIN_OK)
  - Push-Pull Driver
  - Resistor Programmable Threshold Level

2 Applications

- Ultra-Low Power Applications
- 2-Cell and 3-Cell Alkaline-Powered Applications
- Energy Harvesting
- Solar Chargers
- Thermal Electric Generator (TEG) Harvesting
- Wireless Sensor Networks (WSN)
- Low-Power Wireless Monitoring
- Environmental Monitoring
- Bridge and Structural Health Monitoring (SHM)
- Smart Building Controls
- Portable and Wearable Health Devices
- Entertainment System Remote Controls

3 Description

The TPS6273x family provides a highly integrated ultra low power buck converter solution that is well suited for meeting the special needs of ultra-low power applications such as energy harvesting. The TPS6273x provides the system with an externally programmable regulated supply to preserve the overall efficiency of the power-management stage compared to a linear step-down converter. This regulator is intended to step-down the voltage from an energy storage element such as a battery or super capacitor to supply the rail to low-voltage electronics. The regulated output has been optimized to provide high efficiency across low-output currents (<10 µA) to high currents (200 mA).

The TPS6273x integrates an optimized hysteretic controller for low-power applications. The internal circuitry uses a time-based sampling system to reduce the average quiescent current.

Device Information(1)

PART NUMBER	PACKAGE	BODY SIZE (NOM)
TPS6273x	VQFN (14)	3.50 mm × 3.50 mm

(1) For all available packages, see the orderable addendum at the end of the datasheet.



Efficiency vs Output Current



An IMPORTANT NOTICE at the end of this data sheet addresses availability, warranty, changes, use in safety-critical applications, intellectual property matters and other important disclaimers. UNLESS OTHERWISE NOTED, this document contains PRODUCTION DATA.

Table of Contents

1 Features ... 1
2 Applications ... 1
3 Description ... 1
4 Revision History ... 2
5 Description (continued) ... 3
6 Device Voltage Options ... 3
7 Pin Configuration and Functions ... 4
8 Specifications ... 5
8.1 Absolute Maximum Ratings ... 5
8.2 Handling Ratings ... 5
8.3 Recommended Operating Conditions ... 5
8.4 Thermal Information ... 5
8.5 Electrical Characteristics ... 6
8.6 Typical Characteristics ... 8
9 Detailed Description ... 18
9.1 Overview ... 18
9.2 Functional Block Diagram ... 18
9.3 Feature Description ... 18
9.4 Device Functional Modes ... 20
10 Application and Implementation ... 21
10.1 Application Information ... 21
10.2 Typical Applications ... 21
11 Power Supply Recommendations ... 28
12 Layout ... 28
12.1 Layout Guidelines ... 28
12.2 Layout Example ... 28
13 Device and Documentation Support ... 29
13.1 Device Support ... 29
13.2 Related Links ... 29
13.3 Trademarks ... 29
13.4 Electrostatic Discharge Caution ... 29
13.5 Glossary ... 29
14 Mechanical, Packaging, and Orderable Information ... 29

4 Revision History

Changes from Revision B (July 2013) to Revision C	Page
• Added ESD Ratings table, Feature Description section, Device Functional Modes, Application and Implementation section, Power Supply Recommendations section, Layout section, Device and Documentation Support section, and Mechanical, Packaging, and Orderable Information section.	1

Changes from Revision A (March 2013) to Revision B	Page
• Added the TPS62737 Pinout information	4
• Added graphs for TPS62737 to the Typical Characteristics	13
• Added the TPS62737 Application Circuit.	21
• Changed Figure 72	28
• Added Figure 73	28

Changes from Original (October 2012) to Revision A	Page
• Changed the device From: Preview To: Active	1

Copyright © 2012–2014, Texas Instruments Incorporated

5 Description (continued)

To further assist users in the strict management of their energy budgets, the TPS6273x toggles the input power-good indicator to signal an attached microprocessor when the voltage on the input supply has dropped below a preset critical level. This signal is intended to trigger the reduction of load currents to prevent the system from entering an undervoltage condition. In addition, independent enable signals allow the system to control whether the converter is regulating the output, monitoring only the input voltage, or to shut down in an ultra-low quiescent sleep state.

The input power-good threshold and output regulator levels are programmed independently through external resistors.

All the capabilities of TPS6273x are packed into a small footprint 14-lead 3.5-mm × 3.5-mm QFN package (RGY).

6 Device Voltage Options

PART NO.	OUTPUT VOLTAGE	MAX OUTPUT CURRENT	INPUT UVLO
TPS62736 (1)	Resistor Programmable	50 mA	2 V
TPS62737 (1)	Resistor Programmable	200 mA	2 V

(1) The RGY package is available in tape on reel. Add R suffix to order quantities of 3000 parts per reel, T suffix for 250 parts per reel.

7 Pin Configuration and Functions





Pin Functions

PIN				DESCRIPTION
NAME	TPS62736 RGY	TPS62737 RGY	TYPE	
EN1	5	5	Input	Digital input for chip enable, standby, and ship-mode. EN1 = 1 sets ship mode independent of EN2. EN1=0, EN2 = 0 disables the buck converter and sets standby mode. EN1=0, EN2=1 enables the buck converter. Do not leave either pin floating.
EN2	6	6	Input	
IN	1	1	Input	Input supply to the buck regulator
NC	2, 3, 4, 14	4, 14	Input	Connect to VSS
OUT	11	11	Output	Step down (buck) regulator output
SW	13	2, 13	Input	Inductor connection to switching node
Thermal Pad	15	15	Input	Connect to VSS
VIN_OK	10	10	Output	Push-pull digital output for power-good indicator for the input voltage. Pulled up to VIN pin.
VIN_OK_SET	8	8	Input	Resistor divider input for VIN_OK threshold. Pull to VIN to disable. Do not leave pin floating.
VOUT_SET	9	9	Input	Resistor divider input for VOUT regulation level
VRDIV	7	7	Output	Resistor divider biasing voltage
VSS	12	3, 12	Input	Ground connection for the device

Copyright © 2012–2014, Texas Instruments Incorporated

8 Specifications

8.1 Absolute Maximum Ratings(1)(2)

over operating free-air temperature range (unless otherwise noted)

			MIN	MAX	UNIT
	Pin voltage	Input voltage range on IN, EN1, EN2, VRDIV, VIN_OK_SET, VOUT_SET, VIN_OK, OUT, SW,NC	–0.3	5.5	V
TPS62736	Peak currents	IN, OUT		100	mA
TPS62737	Peak currents	IN, OUT		370	mA
T_J	Temperature range	Operating junction temperature range	–40	125	°C

(1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions* is not implied. Exposure to absolute–maximum–rated conditions for extended periods may affect device reliability.
(2) All voltage values are with respect to VSS/ground terminal

8.2 Handling Ratings

			MIN	MAX	UNIT
T_{stg}	Storage temperature range		–65	150	°C
$V_{(ESD)}$	Electrostatic discharge	Human body model (HBM), per ANSI/ESDA/JEDEC JS-001, all pins(1)	-1	1	kV
		Charged device model (CDM), per JEDEC specification JESD22-C101, all pins(2)	-500	500	V
		Machine Model (MM)	-150	150	

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.
(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

8.3 Recommended Operating Conditions

		MIN	NOM	MAX	UNIT
IN	IN voltage range	2		5.5	V
C_{IN}	TPS62736 Input Capacitance	4.7			µF
	TPS62737 Input Capacitance	22			
C_{OUT}	Output Capacitance	10	22		µF
R_1 + R_2 + R_3	Total Resistance for setting reference voltage		13		MΩ
L_{BUCK}	TPS62736 Inductance	4.7	10		µH
	TPS62737 Inductance	10			
T_A	TPS62736 Operating free air ambient temperature	–40		85	°C
	TPS62737 Operating free air ambient temperature	–20		85	
T_J	Operating junction temperature	–40		105	°C

8.4 Thermal Information

THERMAL METRIC(1)		TPS6273x RGY 14 PINS	UNIT
θ_{JA}	Junction-to-ambient thermal resistance	33.7	°C/W
θ_{JCtop}	Junction-to-case (top) thermal resistance	37.6	
θ_{JB}	Junction-to-board thermal resistance	10.1	
ψ_{JT}	Junction-to-top characterization parameter	0.4	
ψ_{JB}	Junction-to-board characterization parameter	10.3	
θ_{JCbot}	Junction-to-case (bottom) thermal resistance	2.9	

(1) For more information about traditional and new thermal metrics, see the IC Package Thermal Metrics application report (SPRA953).

Copyright © 2012–2014, Texas Instruments Incorporated

8.5 Electrical Characteristics

Over recommended ambient temperature range, typical values are at T_A = 25°C. Unless otherwise noted, specifications apply for conditions of V_{IN} = 4.2 V, V_{OUT} = 1.8 V External components, C_{IN} = 4.7 µF for TPS62736 and 22 µF for TPS62737, L_{BUCK} = 10 µH, C_{OUT} = 22 µF.

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
QUIESCENT CURRENTS						
I_Q	TPS62736 Buck enabled state (EN1 = 0, EN2 = 1)	V_{IN} = 2 V, No load on V_{OUT}		380	550	nA
	TPS62736 Buck disabled VIN_OK active state (EN1 = 0, EN2 = 0)			340	520	
	TPS62736 Ship mode state (EN1 = 1, EN2 = x)			10	65	
	TPS62737 Buck enabled state (EN1 = 0, EN2 = 1)			375	600	nA
	TPS62737 Buck disabled VIN_OK active state (EN1 = 0, EN2 = 0)			345	560	
	TPS62737 Ship mode state (EN1 = 1, EN2 = x)			11	45	
OUTPUT						
V_{BIAS}	Output regulation reference		1.205	1.21	1.217	V
V_{OUT}	TPS62736 Output regulation (*Spec does not include the resistor accuracy error*)	I_{OUT} = 10 mA; 1.3 V < V_{OUT} < 3.3 V	–2%	0%	2%	
	TPS62737 Output regulation (*Spec does not include the resistor accuracy error*)	I_{OUT} = 100 mA; 1.3 V < V_{OUT} < 3.3 V;	–2%	0%	2%	
	TPS62736 Output line regulation	I_{OUT} = 100 µA; V_{IN} = 2.4 V to 5.5 V		0.01		%/V
	TPS62737 Output line regulation	I_{OUT} = 10 mA; V_{IN} = 2.3 V to 5.5 V		0.31		
	TPS62736 Output load regulation	I_{OUT} = 100 µA to 50 mA, V_{IN} = 2.2 V		0.01		%/mA
	TPS62737 Output load regulation	I_{OUT} = 100 µA to 200 mA, V_{IN} = 2.2 V; –20°C < T_A < 85°C		0.01		%/mA
	TPS62736 Output ripple	V_{IN} = 4.2V, I_{OUT} = 1 mA, C_{OUT} = 22 µF		20		mVpp
	TPS62737 Output ripple	V_{IN} = 4.2 V, I_{OUT} = 1 mA, C_{OUT} = 22 µF		40		mVpp
	Programmable voltage range for output voltage threshold	I_{OUT} = 10 mA	1.3		V_{IN} – 0.2	V
V_{DO}	TPS62736 Drop-out-voltage when V_{IN} is less than $V_{OUT(SET)}$	V_{IN} = 2.1 V, $V_{OUT(SET)}$ = 2.5 V, I_{OUT} = 10 mA, 100% duty cycle		24	30	mV
	TPS62737 Drop-out-voltage when V_{IN} is less than $V_{OUT(SET)}$	V_{IN} = 2.1 V, $V_{OUT(SET)}$ = 2.5 V, I_{OUT} = 100 mA, 100% duty cycle		180	220	mV
$t_{START-STBY}$	Startup time with EN1 low and EN2 transition to high (Standby Mode)	TPS62736, C_{OUT} = 22 µF		400		µs
		TPS62737, C_{OUT} = 22 µF		300		µs
$t_{START-SHIP}$	Startup time with EN2 high and EN1 transition from high to low (Ship Mode)	C_{OUT} = 22 µF		100		ms

Copyright © 2012–2014, Texas Instruments Incorporated

Electrical Characteristics (continued)

Over recommended ambient temperature range, typical values are at T_A = 25°C. Unless otherwise noted, specifications apply for conditions of V_{IN} = 4.2 V, V_{OUT} = 1.8 V External components, C_{IN} = 4.7 µF for TPS62736 and 22 µF for TPS62737, L_{BUCK} = 10 µH, C_{OUT} = 22 µF.

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
POWER SWITCH						
$R_{DS(on)}$	TPS62736 High-side switch ON resistance	V_{IN} = 3 V		2.4	3	Ω
	TPS62736 Low-side switch ON resistance	V_{IN} = 3 V		1.1	1.5	Ω
	TPS62737 High-side switch ON resistance	V_{IN} = 2.1 V		1.8	2.2	Ω
	TPS62737 Low-side switch ON resistance	V_{IN} = 2.1 V		0.9	1.3	Ω
I_{LIM}	TPS62736 Cycle-by-cycle current limit	2.4 V < V_{IN} < 5.25 V; 1.3 V < V_{OUT} < 3.3 V	68	86	100	mA
	TPS62737 Cycle-by-cycle current limit	2.4 V < V_{IN} < 5.25 V; 1.3 V < V_{OUT} < 3.3 V; –20°C < T_A < 85°C	295	340	370	mA
f_{SW}	Max switching frequency			2		MHz
INPUT						
$V_{IN-UVLO}$	Input under voltage protection	V_{IN} falling	1.91	1.95	2	V
V_{IN-OK}	Input power-good programmable voltage range		2		5.5	V
$V_{IN-OK-ACC}$	TPS62736 Accuracy of V_{IN-OK} setting	V_{IN} increasing	–2%		2%	
	TPS62737 Accuracy of V_{IN-OK} setting		–3%		3%	
$V_{IN-OK-HYS}$	Fixed hysteresis on VIN_OK threshold, OK_HYST	V_{IN} increasing		40		mV
V_{IN_OK-OH}	V_{IN-OK} output high threshold voltage	Load = 10 µA	V_{IN} – 0.2			V
V_{IN_OK-OL}	V_{IN-OK} output low threshold voltage				0.1	V
EN1 and EN2						
V_{IH}	Voltage for EN High setting. Relative to V_{IN}	V_{IN} = 4.2 V	V_{IN} – 0.2			V
V_{IL}	Voltage for EN Low setting				0.2	V

Copyright © 2012–2014, Texas Instruments Incorporated

8.6 Typical Characteristics

Table 1. Table of Graphs for TPS62736

Unless otherwise noted, graphs were taken using Figure 62 with L = Toko 10 µH DFE252012C			FIGURE
η	V_O = 2.5 V Efficiency	vs Output Current	Figure 1
		vs Input Voltage	Figure 2
	V_O = 1.8 V Efficiency	vs Output Current	Figure 3
		vs Input Voltage	Figure 4
	V_O = 1.3 V Efficiency	vs Output Current	Figure 5
		vs Input Voltage	Figure 6
V_{OUT} (DC)	V_O = 2.5 V	vs Output Current	Figure 7
		vs Input Voltage	Figure 8
		vs Temperature	Figure 9
	V_O = 1.8 V	vs Output Current	Figure 10
		vs Input Voltage	Figure 11
		vs Temperature	Figure 12
	V_O = 1.3 V	vs Output Current	Figure 13
		vs Input Voltage	Figure 14
		vs Temperature	Figure 15
I_{OUT} MAX (DC)	V_O = 2.5 V	vs Input Voltage	Figure 16
	V_O = 1.8 V		Figure 17
	V_O = 1.3 V		Figure 18
Input IQ	EN1 = 1, EN2 = 0 (Ship Mode)	vs Input Voltage	Figure 19
	EN1 = 0, EN2 = 0 (Standby Mode)		Figure 20
	EN1 = 0, EN2 = 1 (Active Mode)		Figure 21
Switching Frequency	V_O = 2.5 V	vs Output Current	Figure 23
		vs Input Voltage	Figure 24
Output Ripple	V_O = 2.5 V	vs Output Current	Figure 25
		vs Input Voltage	Figure 26



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 1. Efficiency vs Output Current, V_{OUT} = 2.5 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 2. Efficiency vs Input Voltage, V_{OUT} = 2.5 V

Copyright © 2012–2014, Texas Instruments Incorporated



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 3. Efficiency vs Output Current, V_{OUT} = 1.8 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 4. Efficiency vs Input Voltage, V_{OUT} = 1.8 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 5. Efficiency vs Output Current, V_{OUT} = 1.3 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 6. Efficiency vs Input Voltage, V_{OUT} = 1.3 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 7. Output Voltage vs Output Current. V_{OUT} = 2.5 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 8. Output Voltage vs Input Voltage, V_{OUT} = 2.5 V

Copyright © 2012–2014, Texas Instruments Incorporated



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Thermal stream provided temperature variation

Figure 9. Output Voltage vs Temperature, V_{OUT} = 2.5 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 10. Output Voltage vs Output Current, V_{OUT} = 1.8 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 11. Output Voltage vs Input Voltage, V_{OUT} = 1.8 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Thermal stream provided temperature variation

Figure 12. Output Voltage vs Temperature, V_{OUT} = 1.8 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 13. Output Voltage vs Output Current, V_{OUT} = 1.3 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 14. Output Voltage vs Input Voltage, V_{OUT} = 1.3 V

Copyright © 2012–2014, Texas Instruments Incorporated



IN = Sourcemeter configured as voltage source and measuring current

VOUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Thermal stream provided temperature variation

Figure 15. Output Voltage vs Temperature, V_{OUT} = 1.3 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to increasingly sink current until V(OUT) < VOUT - 100 mV

Thermal stream provided temperature variation

Figure 16. Maximum Output Current vs Input Voltage, V_{OUT} = 2.5 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to increasingly sink current until V(OUT) < VOUT - 100 mV

Thermal stream provided temperature variation

Figure 17. Maximum Output Current vs Input Voltage, V_{OUT} = 1.8 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to increasingly sink current until V(OUT) < VOUT - 100 mV

Thermal stream provided temperature variation

Figure 18. Maximum Output Current vs Input Voltage, V_{OUT} = 1.3 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = open; EN1 = high; EN2 = x

Thermal stream provided temperature variation

Figure 19. Input Quiescent Current vs Input Voltage Ship Mode



IN = Sourcemeter configured as voltage source and measuring current

OUT = open; EN1 = EN2 = low

Thermal stream provided temperature variation

Figure 20. Input Quiescent Current vs Input Voltage Standby Mode



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as voltage source > VOUT to prevent switching

Thermal stream provided temperature variation

Figure 21. Input Quiescent Current vs Input Voltage Active Mode



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as voltage source > VOUT to prevent switching

Thermal stream provided temperature variation

Figure 22. Input Quiescent Current vs Input Voltage Active Mode where R_{SUM} = R1 + R2 + R3



IN = Sourcemeter configured as voltage source

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 23. Major Switching Frequency vs Output Current



IN = Sourcemeter configured as voltage source

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 24. Major Switching Frequency vs Input Voltage



IN = Sourcemeter configured as voltage source

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Scope probe with small ground lead used to measure ripple across COUT

Figure 25. Output Voltage Ripple vs Output Current



IN = Sourcemeter configured as voltage source

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Scope probe with small ground lead used to measure ripple across COUT

Figure 26. Output Voltage Ripple vs Input Voltage

Copyright © 2012–2014, Texas Instruments Incorporated

Table 2. Table of Graphs for TPS62737

Unless otherwise noted, graphs were taken using Figure 52 with L = Toko 10 µH DFE252012C			FIGURE
η	V_O = 2.5 V Efficiency	vs Output Current	Figure 27
		vs Input Voltage	Figure 28
	V_O = 1.8 V Efficiency	vs Output Current	Figure 29
		vs Input Voltage	Figure 30
	V_O = 1.3 V Efficiency	vs Output Current	Figure 31
		vs Input Voltage	Figure 32
V_{OUT} (DC)	V_O = 2.5 V	vs Output Current	Figure 33
		vs Input Voltage	Figure 33
		vs Temperature	Figure 35
	V_O = 1.8 V	vs Output Current	Figure 36
		vs Input Voltage	Figure 37
		vs Temperature	Figure 38
	V_O = 1.3 V	vs Output Current	Figure 39
		vs Input Voltage	Figure 40
		vs Temperature	Figure 41
I_{OUT} MAX (DC)	V_O = 2.5 V	vs Input Voltage	Figure 42
	V_O = 1.8 V		Figure 43
	V_O = 1.3 V		Figure 44
Input IQ	EN1 = 1, EN2 = 0 (Ship Mode)	vs Input Voltage	Figure 45
	EN1 = 0, EN2 = 0 (Standby Mode)		Figure 46
	EN1 = 0, EN2 = 1 (Active Mode)		Figure 47
Switching Frequency	V_O = 1.8 V	vs Output Current	Figure 48
		vs Input Voltage	Figure 49
Output Ripple	V_O = 1.8 V	vs Output Current	Figure 51
		vs Input Voltage	Figure 51



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 27. Efficiency vs Output Current, V_{OUT} = 2.5 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 28. Efficiency vs Input Voltage, V_{OUT} = 2.5 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 29. Efficiency vs Output Current, V_{OUT} = 1.8 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 30. Efficiency vs Input Voltage, V_{OUT} = 1.8 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 31. Efficiency vs Output Current, V_{OUT} = 1.3 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 32. Efficiency vs Input Voltage, V_{OUT} = 1.3 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 33. Output Voltage vs Output Current. V_{OUT} = 2.5 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 34. Output Voltage vs Input Voltage, V_{OUT} = 2.5 V

Copyright © 2012–2014, Texas Instruments Incorporated



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Thermal stream provided temperature variation

Figure 35. Output Voltage vs Temperature, V_{OUT} = 2.5 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 36. Output Voltage vs Output Current, V_{OUT} = 1.8 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 37. Output Voltage vs Input Voltage, V_{OUT} = 1.8 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Thermal stream provided temperature variation

Figure 38. Output Voltage vs Temperature, V_{OUT} = 1.8 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 39. Output Voltage vs Output Current, V_{OUT} = 1.3 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 40. Output Voltage vs Input Voltage, V_{OUT} = 1.3 V

Copyright © 2012–2014, Texas Instruments Incorporated



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Thermal stream provided temperature variation

Figure 41. Output Voltage vs Temperature, V_{OUT} = 1.3 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to increasingly sink current until V(OUT) < VOUT - 100 mV

Thermal stream provided temperature variation

Figure 42. Maximum Output Current vs Input Voltage V_{OUT} = 2.5 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to increasingly sink current until V(OUT) < VOUT - 100 mV

Thermal stream provided temperature variation

Figure 43. Maximum Output Current vs Input Voltage, V_{OUT} = 1.8 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as current source to increasingly sink current until V(OUT) < VOUT - 100 mV

Thermal stream provided temperature variation

Figure 44. Maximum Output Current vs Input Voltage, V_{OUT} = 1.3 V



IN = Sourcemeter configured as voltage source and measuring current

OUT = open; EN1 = high; EN2 = x

Thermal stream provided temperature variation

Figure 45. Input Quiescent Current vs Input Voltage Ship Mode



IN = Sourcemeter configured as voltage source and measuring current

OUT = open; EN1 = EN2 = low

Thermal stream provided temperature variation

Figure 46. Input Quiescent Current vs Input Voltage Standby Mode

Copyright © 2012–2014, Texas Instruments Incorporated



IN = Sourcemeter configured as voltage source and measuring current

OUT = sourcemeter configured as voltage source > VOUT to prevent switching

Thermal stream provided temperature variation

Figure 47. Input Quiescent Current vs Input Voltage Active Mode



IN = Sourcemeter configured as voltage source

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 48. Major Switching Frequency vs Output Current



IN = Sourcemeter configured as voltage source

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Figure 49. Major Switching Frequency vs Input Voltage



IN = Sourcemeter configured as voltage source

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Scope probe with small ground lead used to measure ripple across COUT

Figure 50. Output Voltage Ripple vs Output Current



IN = Sourcemeter configured as voltage source

OUT = sourcemeter configured as current source to sink current and VCOMP > VOUT

Scope probe with small ground lead used to measure ripple across COUT

Figure 51. Output Voltage Ripple vs Input Voltage

9 Detailed Description

9.1 Overview

The TPS6273x family provides a highly integrated ultra low power buck converter solution that is well suited for meeting the special needs of ultra-low power applications such as energy harvesting. The TPS6273x provides the system with an externally programmable regulated supply in order to preserve the overall efficiency of the power-management stage compared to a linear step down converter. This regulator is intended to step-down the voltage from an energy storage element such as a battery or super capacitor in order to supply the rail to low-voltage electronics. The regulated output has been optimized to provide high efficiency across low-output currents (<10 µA) to high currents (200 mA).

The TPS6273x integrates an optimized hysteretic controller for low-power applications. The internal circuitry uses a time-based sampling system to reduce the average quiescent current.

9.2 Functional Block Diagram



9.3 Feature Description

9.3.1 Step-Down (Buck) Converter Operation

The buck regulator in the TPS6273x takes input power from VIN, steps it down and provides a regulated voltage at the OUT pin. It employs pulse frequency modulation (PFM) control to regulate the voltage close to the desired reference voltage. The reference voltage is set by the user programmed resistor divider. The current through the inductor is controlled through internal current sense circuitry. The peak current in the inductor is controlled to maintain high efficiency of the converter across a wide input current range. The TPS62736 converter delivers an average output current of 50mA with a peak inductor current of 100 mA. The TPS62737 converter delivers an average output current of 200 mA with a peak inductor current of 370 mA. The buck regulator is disabled when

Copyright © 2012–2014, Texas Instruments Incorporated

Feature Description (continued)

the voltage on VIN reaches the UVLO condition. The UVLO level is continuously monitored. The buck regulator continues to operate in pass (100% duty cycle) mode, passing the input voltage to the output, as long as VIN is greater than UVLO and less than VIN minus I_{OUT} times $R_{DS(on)}$ of the high-side FET (that is, VIN – I_{OUT} x $R_{DS(on)-HS}$). In order to save power from being dissipated through other ICs on this supply rail while allowing for a faster wake up time, the buck regulator can be enabled and disabled through the EN2 pin for systems that desire to completely turn off the regulated output.

9.3.2 Programming OUT Regulation Voltage and VIN_OK

To set the proper output-regulation voltage and input voltage power-good comparator, the external resistors must be carefully selected. Figure 62 illustrates an application diagram which uses the minimal resistor count for setting both VOUT and VIN_OK. Note that VBIAS is nominally 1.21 V per the electrical specification table. Referring to Figure 52, the OUT DC set point is given by Equation 1.

$$VOUT = VBIAS\left(\frac{R_1 + R_2 + R_3}{R_1 + R_2}\right) \tag{1}$$

The VIN_OK setting is given by Equation 2.

$$VIN_OK = VBIAS\left(\frac{R_1 + R_2 + R_3}{R_1}\right) \tag{2}$$

The sum of the resistors is recommended to be no greater than 13 MΩ, that is, RSUM = R1 + R2 + R3 = 13 MΩ. Due to the sampling operation of the output resistors, lowering RSUM only increases quiescent current slightly as can be seen in Figure 22. Higher resistors may result in poor output voltage regulation and/or input voltage power-good threshold accuracies due to noise pickup through the high-impedance pins or reduction of effective resistance due to parasitic resistance created from board assembly residue. See *Layout* for more details.

If it is preferred to separate the VOUT and VIN_OK resistor strings, two separate strings of resistors could be used as shown in Figure 62. The OUT DC set point is then given by Equation 3.

$$VOUT = VBIAS\left(\frac{R_3 + R_4}{R_4}\right) \tag{3}$$

The VIN_OK setting is then given by Equation 4.

$$VIN_OK = VBIAS\left(\frac{R_1 + R_2}{R_1}\right) \tag{4}$$

If it is preferred to disable the VIN_OK setting, the VIN_OK_SET pin can be tied to VIN. To set VOUT in this configuration, use Equation 3. To tighten the DC set point accuracy, use external resistors with better than 1% resistor tolerance. Because output voltage ripple has a large effect on input line regulation and the output load regulation, using a larger output capacitor will improve both line and load regulation.

9.3.3 Nano-Power Management and Efficiency

The high efficiency of the TPS6273x is achieved through the proprietary Nano-Power management circuitry and algorithm. This feature essentially samples and holds all references in order to reduce the average quiescent current. That is, the internal circuitry is only active for a short period of time and then off for the remaining period of time at the lowest feasible duty cycle. A portion of this feature can be observed in Figure 66 where the VRDIV node is monitored. Here, the VRDIV node provides a connection to the input (larger voltage level) and generates the output reference (lower-voltage level) for a short period of time. The divided down value of input voltage is compared to VBIAS and the output voltage reference is sampled and held to get the VOUT_SET point. Because this biases a resistor string, the current through these resistors is only active when the Nano-Power management circuitry makes the connection — hence, reducing the overall quiescent current due to the resistors. This process repeats every 64 ms. Similarly, the VIN_OK level is monitored every 64 ms, as shown in Figure 55.

Copyright © 2012–2014, Texas Instruments Incorporated

Feature Description (continued)

The efficiency versus output current and efficiency versus input voltage are plotted for three different output voltages for both the TPS62736 and TPS62737 devices in *Typical Characteristics*. All data points were captured by averaging the overall input current. This must be done, due to the periodic biasing scheme implemented through the Nano-Power management circuitry. The input current efficiency data was gathered using a source meter set to average over at least 25 samples and at the highest accuracy sampling rate. Each data point takes a long period of time to gather in order to properly measure the resulting input current when calculating the efficiency.

9.4 Device Functional Modes

9.4.1 Enable Controls

There are two enable pins implemented in the TPS6273x in order to maximize the flexibility of control for the system. The EN1 pin is considered to be the chip enable. If EN1 is set to a 1 then the entire chip is placed into ship mode. If EN1 is 0 then the chip is enabled. EN2 enables and disables the switching of the buck converter. When EN2 is low, the internal circuitry remains ON and the VIN_OK indicator still functions. This can be used to disable down-stream electronics in case of a low input-supply condition. When EN2 is 1, the buck converter operates normally.

Table 3. Enable Functionality Table

EN1 PIN	EN2 PIN	FUNCTIONAL STATE
0	0	Partial standby mode. Buck switching converter is off, but VIN_OK indication is on
0	1	Buck mode and VIN_OK enabled
1	x	Full standby mode. Switching converter and VIN_OK indication is off (ship mode)

9.4.2 Startup Behavior

The TPS6273x has two startup responses: 1) from the ship-mode state (EN1 transitions from high to low), and 2) from the standby state (EN2 transitions from low to high). The first startup response out of the ship-mode state has the longest time duration due to the internal circuitry being disabled. This response is shown in Figure 70 for the TPS62736 and Figure 60 for the TPS62737. The startup time takes approximately 100 ms due to the internal Nano-Power management circuitry needing to complete the 64 ms sample and hold cycle.

Startup from the standby state is shown in Figure 71 for the TPS62736 and Figure 61 for the TPS62737. This response is much faster due to the internal circuitry being pre-enabled. The startup time from this state is entirely dependent on the size of the output capacitor. The larger the capacitor, the longer it will take to charge during startup. The TPS6273x can startup into a prebiased output voltage.

Copyright © 2012–2014, Texas Instruments Incorporated

10 Application and Implementation

NOTE

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

10.1 Application Information

The TPS62736/7 are step down DC-DC converters. Their low quiescent currents make them ideal for battery powered systems that are operated at low duty cycles in order to achieve low total power levels.

10.2 Typical Applications

10.2.1 TPS62737 3-Resistor Typical Application Circuit



Figure 52. TPS62737 3-Resistor Typical Application Circuit

10.2.1.1 Design Requirements

A 1.8-V, up to 200 mA regulated power rail is needed. The VIN_OK comparator should indicate when the input voltage drops below 2.9 V. No large load transients are expected.

10.2.1.2 Detailed Design Procedure

The recommended 10-µH inductor (TOKO DFE252012C) and 22-µF input capacitor are used. Since no large load transients are expected, the minimum 22-µF output capacitor is used. Had a large load transient been expected, we would have sized the capacitor using ITRAN = COUT x ΔVOUT / ΔTIME where ΔVOUT is amount of VOUT droop allowed for the time of the transient.

First set RSUM = R1 + R2 + R3 = 13 MΩ then solve Equation 2 for R1 = VBIAS x RSUM / VIN_OK = 1.21 V x 13 MΩ / 2.9 V = 5.42 MΩ → 5.49 MΩ as the closest 1 % resistor.

Typical Applications (continued)

Then solve Equation 2 for R2 = VBIAS x RSUM / VOUT - R1 = 1.21 V x 13 MΩ / 1.8 V - 5.42 MΩ = 3.32 MΩ → 3.4 MΩ as the closest 1% resistor.

Finally R3 = RSUM - R1 - R2 = 13 MΩ - 5.42 MΩ - 3.32 MΩ = 4.26 MΩ → 4.32 MΩ as the closest 1% resistor.

These values yield VOUT = 1.79 V and VIN_OK threshold = 2.91 V.

If using 4 resistors, see *Resistor Selection* for guidance on sizing the resistors.

10.2.1.2.1 Inductor Selection

The internal-control circuitry is designed to control the switching behavior with a nominal inductance of 10 µH ± 20%. The saturation current of the inductor' should be at least 25% higher than the maximum cycle-by-cycle current limit per the electrical specs table (I_{LIM}) in order to account for load transients. Because this device is a hysteretic controller, it is a naturally stable system (single order transfer function). However, the smaller the inductor value is, the faster the switching currents are. The speed of the peak current detect circuit sets the inductor of the TPS62736 lower bound to 4.7 µH. When using a 4.7 µH, the peak inductor current will increase when compared to that of a 10-µH inductor. The steady-state operation with a 4.7-µH inductor with a 50-mA load for the TPS62736 is shown in Figure 65.

A list of inductors recommended for this device is shown in Table 4.

Table 4. Recommended Inductors

INDUCTANCE (µH)	DIMENSIONS (mm)	PART NUMBER	MANUFACTURER
10	2.0 x 2.5 x 1.2	DFE252012C-H-100M	Toko
10	4.0 x 4.0 x 1.7	LPS4018-103M	Coilcraft
4.7 (TPS62736 only)	2.0 x 2.5 x 1.2	DFE252012R-H-4R7M	Toko

10.2.1.2.2 Output Capacitor Selection

The output capacitor is chosen based on transient response behavior and ripple magnitude. The lower the capacitor value, the larger the ripple will become and the larger the droop will be in the case of a transient response. It is recommended to use at least a 22-µF output capacitor for most applications.

10.2.1.2.3 Input Capacitor Selection

The bulk input capacitance is recommended to be a minimum of 4.7 µF ± 20% for the TPS62736 and 22 µF ± 20% for the TPS62737. This bulk capacitance is used to suppress the lower frequency transients produced by the switching converter. There is no upper bound to the input-bulk capacitance. In addition, a high-frequency bypass capacitor of 0.1 µF is recommended in parallel with the bulk capacitor. The high-frequency bypass is used to suppress the high-frequency transients produced by the switching converter.

10.2.1.2.4 Resistor Selection

Equation 1 to Equation 4 are the equations for sizing the external resistors to set the VIN_OK threshold and VOUT regulation value. The spreadsheet at SLVC489 can help size the external resistors.

10.2.1.3 Application Curves

See efficiency, line regulation, and load regulation curves at Figure 30, Figure 37, and Figure 36.

Copyright © 2012–2014, Texas Instruments Incorporated



V(IN) = 3.6 V bench power supply
R(OUT) = 100 kΩ

Figure 53. Steady State Operation



V(IN) = 3.6 V bench power supply
R(OUT) = 9 Ω

Figure 54. Steady State Operation



V(IN) = power amplifier ramped from 0 V to 5 V to 0 V

Figure 55. Power Management Response



V(IN) = 3.6 V bench power supply + additional C(IN) = 100 uF
R(OUT) = open to 9 Ω to open

Figure 56. Load Transient Response



V(IN) = 3.6 V -> 4.6 V -> 4.6 V from bench power supply
R(OUT) = 9 Ω

Figure 57. Line Transient Response



V(IN) = 4.0 V bench supply + additional C(IN) = 100 uF
VOUT resistors modified to provide 2.5 V
I(OUT) = 200 mA every 1 us

Figure 58. IR Pulse Transient Response



V(IN) = power amplifier ramped from 0 V to 5 V to 0 V
EN1 = low; EN2 = high

Figure 59. Startup Behavior with Slow Ramping VIN



V(IN) = 3.6 V bench power supply
EN2 = high; EN1 transitioned from high to low
R(OUT) = 1 kΩ

Figure 60. Ship-Mode Startup Behavior



V(IN) = 3.6 V bench power supply
EN1 = low; EN2 transitioned from low to high
R(OUT) = 1 kΩ

Figure 61. Standby-Mode Startup Behavior

Copyright © 2012–2014, Texas Instruments Incorporated

10.2.2 TPS62736 4-Resistor Typical Application Circuit



Figure 62. TPS62736 4-Resistor Typical Application Circuit

10.2.2.1 Design Requirements

A 2.5-V, up to 50-mA regulated power rail is needed. The VIN_OK comparator should indicate when the input voltage drops below 2.9 V. No large load transients are expected.

10.2.2.2 Detailed Design Procedure

The recommended 10-µH inductor (TOKO DFE252012C) and 4.7-µF input capacitor are used. Since no large load transients are expected, the minimum 22-µF output capacitor is used. Had a large load transient been expected, we would have sized the capacitor using ITRAN = COUT x ΔVOUT / ΔTIME where ΔVOUT is amount of VOUT droop allowed for the time of the transient.

First set RSUM = R1 + R2 = R3 + R4 = 13 MΩ then solve Equation 4 for R1 = VBIAS x RSUM / VIN_OK = 1.21 V x 13 MΩ / 2.9 V = 5.42 MΩ → 5.36 MΩ as the closest 1 % resistor.

Then R2 = RSUM - R1 = 13 MΩ - 5.42 MΩ = 7.58 MΩ → 7.5 MΩ as the closest 1% resistor.

Solve Equation 3 for R4 = VBIAS x RSUM / VOUT = 1.21 V x 13 MΩ / 2.5 V = 6.29 MΩ → 6.34 MΩ as the closest 1% resistor.

Finally R3 = RSUM - R3 = 13 MΩ - 6.29 MΩ = 6.71 MΩ → 6.81 MΩ as the closest 1% resistor.

These values yield VOUT = 2.51 V and VIN_OK threshold = 2.90 V.

If using 3 resistors, see *Resistor Selection* for guidance on sizing the resistors.

10.2.2.3 Application Curves

See efficiency, load regulation and line regulation graphs at Figure 1, Figure 7 and Figure 8 respectively.



10 µs/div

V(IN) = 3.0 V bench power supply
R(OUT) = 50 Ω

Figure 63. Steady State Operation



2 µs/div

V(IN) = 3.0 V bench power supply
R(OUT) = 100 kΩ

Figure 64. Steady State Operation



4 µs/div

V(IN) = 3.0 V bench power supply
VOUT resistors changed to provide 1.8 V; L = 4.7 uH
R(OUT) = 100 kΩ

Figure 65. Steady State Operation



2 ms/div

V(IN) = 3.0 V bench power supply

Figure 66. Sampling Waveform



40 ms/div

V(IN) = 3.0 V -> 5.0 V from bench power supply
R(OUT) = 50 Ω

Figure 67. Line Transient Response



10 µs/div

V(IN) = 4.0 V from bench power supply + additional CIN = 100 uF
R(OUT) = open - > 50 Ω

Figure 68. Load Transient Response

Copyright © 2012–2014, Texas Instruments Incorporated



4 µs/div

V(IN) = 4.0 V from bench power supply + additional CIN = 100 uF

I(OUT) = 200 mA every 1us

Figure 69. IR Pulse Transient Response



20 ms/div

V(IN) = 4.0 V from bench power supply

VOUT resistors modified to provide 1.8 V

EN2 = high, EN1 transitioned high to low

Figure 70. Ship-Mode Startup Behavior



400 µs/div

V(IN) = 4.0 V from bench power supply

VOUT resistors modified to provide 1.8 V

EN1 = low, EN2 transitioned low to high

Figure 71. Standby-Mode Startup Behavior

11 Power Supply Recommendations

The TPS62736 / 7 ICs require a low impedance power source (e.g. battery, wall adapter) capable of providng between 2.0 V and 5.5 V and up to 100 mA / 370 mA respectively. When the voltage at IN is less than or equal to VOUT, the IC stops switching, turns on the high side FET and provides VOUT = VIN - ILOAD x RDS(on)-HighSideFET.

12 Layout

12.1 Layout Guidelines

To minimize switching noise generation, the step-down converter (buck) power stage external components must be carefully placed. The most critical external component for a buck power stage is its input capacitor. The bulk input capacitor (C_{IN1}) and high frequency decoupling capacitor (C_{IN2}) must be placed as close as possible between the power stage input (IN pin 1) and ground (VSS pin 12). Next, the inductor (L1) must be placed as close as possible beween the switching node (SW pin 13) and the output voltage (OUT pin 11). Finally, the output capacitor (C_{OUT}) should be placed as close as possible between the output voltage (OUT pin 11) and GND (VSS pin 12). In the diagram below, the input and output capacitor grounds are connected to VSS pin 12 through vias to the bottom-layer ground plane of the PCB.

To minimize noise pickup by the high impedance voltage setting nodes (VIN_OK_SET pin 8 and VOUT_SET pin 9), the external resistors (R1, R2 and R3) should be placed so that the traces connecting the midpoints of the string are as short as possible. In the diagram below, the connection to VOUT_SET is by a bottom layer trace.

The remaining pins are either NC pins, that should be connected to the PowerPAD™ as shown below, or digital signals with minimal layout restrictions.

In order to maximize efficiency at light load, the use of voltage level setting resistors > 1 MΩ is recommended. However, during board assembly, contaminants such as solder flux and even some board cleaning agents can leave residue that may form parasitic resistors across the physical resistors and/or from one end of a resistor to ground, especially in humid, fast airflow environments. This can result in the voltage regulation and threshold levels changing significantly from those expected per the installed resistor values. Therefore, it is highly recommended that no ground planes be poured near the voltage setting resistors. In addition, the boards must be carefully cleaned, possibly rotated at least once during cleaning, and then rinsed with de-ionized water until the ionic contamination of that water is well above 50 MΩ. If this is not feasible, then it is recommended that the sum of the voltage setting resistors be reduced to at least 5 times below the measured ionic contamination.

12.2 Layout Example



Figure 72. Recommended Layout, TPS62736



Figure 73. Recommended Layout, TPS62737

Copyright © 2012–2014, Texas Instruments Incorporated

13 Device and Documentation Support

13.1 Device Support

13.1.1 Third-Party Products Disclaimer

TI'S PUBLICATION OF INFORMATION REGARDING THIRD-PARTY PRODUCTS OR SERVICES DOES NOT CONSTITUTE AN ENDORSEMENT REGARDING THE SUITABILITY OF SUCH PRODUCTS OR SERVICES OR A WARRANTY, REPRESENTATION OR ENDORSEMENT OF SUCH PRODUCTS OR SERVICES, EITHER ALONE OR IN COMBINATION WITH ANY TI PRODUCT OR SERVICE.

13.2 Related Links

The table below lists quick access links. Categories include technical documents, support and community resources, tools and software, and quick access to sample or buy.

Table 5. Related Links

PARTS	PRODUCT FOLDER	SAMPLE & BUY	TECHNICAL DOCUMENTS	TOOLS & SOFTWARE	SUPPORT & COMMUNITY
TPS62736	Click here	Click here	Click here	Click here	Click here
TPS62737	Click here	Click here	Click here	Click here	Click here

13.3 Trademarks

PowerPAD is a trademark of Texas Instruments.
All other trademarks are the property of their respective owners.

13.4 Electrostatic Discharge Caution

These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

13.5 Glossary

SLYZ022 — *TI Glossary*.

This glossary lists and explains terms, acronyms, and definitions.

14 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

PACKAGING INFORMATION

Orderable part number	Status (1)	Material type (2)	Package | Pins	Package qty | Carrier	RoHS (3)	Lead finish/ Ball material (4)	MSL rating/ Peak reflow (5)	Op temp (°C)	Part marking (6)
TPS62736RGYR	Active	Production	VQFN (RGY) | 14	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 85	62736
TPS62736RGYR.A	Active	Production	VQFN (RGY) | 14	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 85	62736
TPS62736RGYRG4	Active	Production	VQFN (RGY) | 14	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 85	62736
TPS62736RGYRG4.A	Active	Production	VQFN (RGY) | 14	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 85	62736
TPS62736RGYT	Active	Production	VQFN (RGY) | 14	250 | SMALL T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 85	62736
TPS62736RGYT.A	Active	Production	VQFN (RGY) | 14	250 | SMALL T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 85	62736
TPS62737RGYR	Active	Production	VQFN (RGY) | 14	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 105	62737
TPS62737RGYR.A	Active	Production	VQFN (RGY) | 14	3000 | LARGE T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 105	62737
TPS62737RGYT	Active	Production	VQFN (RGY) | 14	250 | SMALL T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 105	62737
TPS62737RGYT.A	Active	Production	VQFN (RGY) | 14	250 | SMALL T&R	Yes	NIPDAU	Level-2-260C-1 YEAR	-40 to 105	62737

(1) **Status:** For more details on status, see our product life cycle.

(2) **Material type:** When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

(3) **RoHS values:** Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

(4) **Lead finish/Ball material:** Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

(5) **MSL rating/Peak reflow:** The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

(6) **Part marking:** There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative

and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

TAPE AND REEL INFORMATION

REEL DIMENSIONS



TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
TPS62736RGYR	VQFN	RGY	14	3000	330.0	12.4	3.75	3.75	1.15	8.0	12.0	Q2
TPS62736RGYRG4	VQFN	RGY	14	3000	330.0	12.4	3.75	3.75	1.15	8.0	12.0	Q2
TPS62736RGYT	VQFN	RGY	14	250	180.0	12.4	3.75	3.75	1.15	8.0	12.0	Q2
TPS62737RGYR	VQFN	RGY	14	3000	330.0	12.4	3.75	3.75	1.15	8.0	12.0	Q2
TPS62737RGYT	VQFN	RGY	14	250	180.0	12.4	3.75	3.75	1.15	8.0	12.0	Q2

TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
TPS62736RGYR	VQFN	RGY	14	3000	346.0	346.0	33.0
TPS62736RGYRG4	VQFN	RGY	14	3000	346.0	346.0	33.0
TPS62736RGYT	VQFN	RGY	14	250	210.0	185.0	35.0
TPS62737RGYR	VQFN	RGY	14	3000	346.0	346.0	33.0
TPS62737RGYT	VQFN	RGY	14	250	210.0	185.0	35.0

GENERIC PACKAGE VIEW

RGY 14

VQFN - 1 mm max height

3.5 x 3.5, 0.5 mm pitch

PLASTIC QUAD FLATPACK - NO LEAD

This image is a representation of the package family, actual package may vary.
Refer to the product data sheet for package details.



4231541/A



NOTES:

1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. The package thermal pad must be soldered to the printed circuit board for thermal and mechanical performance.



LAND PATTERN EXAMPLE
SCALE:20X



SOLDER MASK DETAILS

4219040/A 09/2015

NOTES: (continued)

4. This package is designed to be soldered to a thermal pad on the board. For more information, see Texas Instruments literature number SLUA271 (www.ti.com/lit/slua271).



SOLDER PASTE EXAMPLE
BASED ON 0.125 mm THICK STENCIL

EXPOSED PAD
80% PRINTED SOLDER COVERAGE BY AREA
SCALE:20X

4219040/A 09/2015

NOTES: (continued)

5. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES “AS IS” AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI’s products are provided subject to TI’s Terms of Sale or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI’s provision of these resources does not expand or otherwise alter TI’s applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2025, Texas Instruments Incorporated