

## DS36C200 Dual High Speed Bi-Directional Differential Transceiver

Check for Samples: [DS36C200](#)


### FEATURES

- Optimized for DSS to DVHS Interface Link
- Compatible IEEE 1394 Signaling Voltage Levels
- Operates Above 100 Mbps
- Bi-directional Transceivers
- 14-lead SOIC Package
- Ultra Low Power Dissipation
- $\pm 100$  mV Receiver Sensitivity
- Low Differential Output Swing Typical 210 mV
- High Impedance During Power Off

### DESCRIPTION

The DS36C200 is a dual transceiver device optimized for high data rate and low power applications. This device provides a single chip solution for a dual high speed bi-directional interface. Also, both control pins may be routed together for single bit control of datastreams. Both control pins are adjacent to each other for ease of routing them together. The DS36C200 is compatible with IEEE 1394 physical layer and may be used as an economical solution with some considerations. Please reference the application information on 1394 for more information. The device is in a 14-lead small outline package. The differential driver outputs provides low EMI with its low output swings typically 210 mV. The receiver offers  $\pm 100$  mV threshold sensitivity, in addition to common-mode noise protection.


### Connection Diagram



Note: \* denotes active LOW pin

**Figure 1. SOIC Package**  
See Package Number D (R-PDSO-G14)

### Functional Diagram



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

All trademarks are the property of their respective owners.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of the Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 1998–2013, Texas Instruments Incorporated



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

### Absolute Maximum Ratings<sup>(1)(2)</sup>

|                                               |                              |
|-----------------------------------------------|------------------------------|
| Supply Voltage ( $V_{CC}$ )                   | -0.3V to +6V                 |
| Enable Input Voltage<br>(DE, RE*)             | -0.3V to ( $V_{CC} + 0.3V$ ) |
| Voltage (DI/RO)                               | -0.3V to +5.9V               |
| Voltage (DO/RI±)                              | -0.3V to +5.9V               |
| Maximum Package Power Dissipation @+25°C      |                              |
| M Package                                     | 1255 mW                      |
| Derate M Package                              | 10.04 mW/°C above +25°C      |
| Storage Temperature Range                     | -65°C to +150°C              |
| Lead Temperature Range<br>(Soldering, 4 sec.) | +260°C                       |
| ESD Rating <sup>(3)</sup>                     |                              |
| (HBM, 1.5 kΩ, 100 pF)                         | ≥ 3.5 kV                     |
| (EIAJ, 0 Ω, 200 pF)                           | ≥ 300V                       |

- (1) "Absolute Maximum Ratings" are those values beyond which the safety of the device cannot be ensured. They are not meant to imply that the devices should be operated at these limits. The table of "Electrical Characteristics" specifies conditions of device operation.
- (2) If Military/Aerospace specified devices are required, please contact the TI Sales Office/Distributors for availability and specifications.
- (3) ESD Rating: HBM (1.5 kΩ, 100 pF) ≥ 3.5 kV EIAJ (0Ω, 200 pF) ≥ 300V

### Recommended Operating Conditions

|                                             | Min  | Typ  | Max  | Units |
|---------------------------------------------|------|------|------|-------|
| Supply Voltage ( $V_{CC}$ )                 | +4.5 | +5.0 | +5.5 | V     |
| Receiver Input Voltage                      | 0    |      | 2.4  | V     |
| Operating Free Air<br>Temperature ( $T_A$ ) | 0    | 25   | 70   | °C    |

## Electrical Characteristics<sup>(1)(2)(3)</sup>

Over supply voltage and operating temperature ranges, unless otherwise specified

| Symbol                                                            | Parameter                        | Conditions                                           | Pin             | Min  | Typ  | Max             | Units |
|-------------------------------------------------------------------|----------------------------------|------------------------------------------------------|-----------------|------|------|-----------------|-------|
| <b>DIFFERENTIAL DRIVER CHARACTERISTICS (RE* = V<sub>CC</sub>)</b> |                                  |                                                      |                 |      |      |                 |       |
| V <sub>OD</sub>                                                   | Output Differential Voltage      | R <sub>L</sub> = 55Ω, (Figure 2)                     | DO+,<br>DO–     | 172  | 210  | 285             | mV    |
| ΔV <sub>OD</sub>                                                  | V <sub>OD</sub> Magnitude Change |                                                      |                 | 0    | 4    | 35              | mV    |
| V <sub>OH</sub>                                                   | Output High Voltage              |                                                      |                 |      | 1.36 |                 | V     |
| V <sub>OL</sub>                                                   | Output Low Voltage               |                                                      |                 |      | 1.15 |                 | V     |
| V <sub>OS</sub>                                                   | Offset Voltage                   |                                                      |                 | 1.0  | 1.25 | 1.6             | V     |
| ΔV <sub>OS</sub>                                                  | Offset Magnitude Change          |                                                      |                 | 0    | 5    | 25              | mV    |
| I <sub>OZD</sub>                                                  | TRI-STATE Leakage                | V <sub>OUT</sub> = V <sub>CC</sub> or GND            |                 | –10  | ±1   | +10             | μA    |
| I <sub>OXD</sub>                                                  | Power-Off Leakage                | V <sub>OUT</sub> = 5.5V or GND, V <sub>CC</sub> = 0V |                 | –10  | ±1   | +10             | μA    |
| I <sub>OSD</sub>                                                  | Output Short Circuit Current     | V <sub>OUT</sub> = 0V                                |                 |      | –4   | –9              | mA    |
| <b>DIFFERENTIAL RECEIVER CHARACTERISTICS (DE = GND)</b>           |                                  |                                                      |                 |      |      |                 |       |
| V <sub>TH</sub>                                                   | Input Threshold High             | V <sub>CM</sub> = 0V to 2.3V                         | RI+,<br>RI–     |      |      | +100            | mV    |
| V <sub>TL</sub>                                                   | Input Threshold Low              |                                                      |                 | –100 |      |                 | mV    |
| I <sub>IN</sub>                                                   | Input Current                    | V <sub>IN</sub> = +2.4V or 0V                        |                 | –10  | ±1   | +10             | μA    |
| V <sub>OH</sub>                                                   | Output High Voltage              | I <sub>OH</sub> = –400 μA                            | RO              | 3.8  | 4.9  |                 | V     |
|                                                                   |                                  | Inputs Open                                          |                 | 3.8  | 4.9  |                 | V     |
|                                                                   |                                  | Inputs Terminated, R <sub>t</sub> = 55Ω              |                 | 3.8  | 4.9  |                 | V     |
|                                                                   |                                  | Inputs Shorted, V <sub>ID</sub> = 0V                 |                 |      | 4.9  |                 | V     |
| V <sub>OL</sub>                                                   | Output Low Voltage               | I <sub>OL</sub> = 2.0 mA, V <sub>ID</sub> = –200 mV  |                 |      | 0.1  | 0.4             | V     |
| I <sub>OSR</sub>                                                  | Output Short Circuit Current     | V <sub>OUT</sub> = 0V                                |                 | –15  | –60  | –100            | mA    |
| <b>DEVICE CHARACTERISTICS</b>                                     |                                  |                                                      |                 |      |      |                 |       |
| V <sub>IH</sub>                                                   | Input High Voltage               |                                                      | DI, DE<br>RE*   | 2.0  |      | V <sub>CC</sub> | V     |
| V <sub>IL</sub>                                                   | Input Low Voltage                |                                                      |                 | GND  |      | 0.8             | V     |
| I <sub>IH</sub>                                                   | Input High Current               | V <sub>IN</sub> = V <sub>CC</sub> or 2.4V            |                 |      | ±1   | ±10             | μA    |
| I <sub>IL</sub>                                                   | Input Low Current                | V <sub>IN</sub> = GND or 0.4V                        |                 |      | ±1   | ±10             | μA    |
| V <sub>CL</sub>                                                   | Input Clamp Voltage              | I <sub>CL</sub> = –18 mA                             |                 | –1.5 | –0.8 |                 | V     |
| I <sub>CCD</sub>                                                  | Power Supply Current             | No Load, DE = RE* = V <sub>CC</sub>                  | V <sub>CC</sub> |      | 3    | 7               | mA    |
|                                                                   |                                  | R <sub>L</sub> = 55Ω, DE = RE* = V <sub>CC</sub>     |                 |      | 11   | 17              | mA    |
|                                                                   |                                  | DE = RE* = 0V                                        |                 |      | 6    | 10              | mA    |
| I <sub>CCR</sub>                                                  |                                  |                                                      |                 |      |      |                 |       |

- (1) Current into device pins is defined as positive. Current out of device pins is defined as negative. All voltages are referenced to ground except V<sub>OD</sub> and V<sub>ID</sub>.
- (2) All typicals are given for V<sub>CC</sub> = +5.0V and T<sub>A</sub> = +25°C.
- (3) The DS36C200 is a current mode device and only function with datasheet specification when a resistive load is applied to the drivers outputs.

## Switching Characteristics

Over supply voltage and operating temperature ranges, unless otherwise specified. <sup>(1)</sup> <sup>(2)</sup>

| Symbol                                | Parameter                                                | Conditions                                                                  | Min | Typ | Max | Units |
|---------------------------------------|----------------------------------------------------------|-----------------------------------------------------------------------------|-----|-----|-----|-------|
| DIFFERENTIAL DRIVER CHARACTERISTICS   |                                                          |                                                                             |     |     |     |       |
| t <sub>PHLD</sub>                     | Differential Propagation Delay High to Low               | R <sub>L</sub> = 55Ω, C <sub>L</sub> = 10 pF<br>(Figure 3 and Figure 4)     | 1.0 | 2.5 | 5.5 | ns    |
| t <sub>PLHD</sub>                     | Differential Propagation Delay Low to High               |                                                                             | 1.0 | 2.6 | 5.5 | ns    |
| t <sub>SKD</sub>                      | Differential Skew  t <sub>PHLD</sub> – t <sub>PLHD</sub> |                                                                             | 0   | 0.1 | 2   | ns    |
| t <sub>TLH</sub>                      | Transition Time Low to High                              |                                                                             | 0   | 0.5 | 2   | ns    |
| t <sub>THL</sub>                      | Transition Time High to Low                              |                                                                             | 0   | 0.5 | 2   | ns    |
| t <sub>PHZ</sub>                      | Disable Time High to Z                                   | R <sub>L</sub> = 55Ω<br>(Figure 5 and Figure 6)                             | 0.3 | 5   | 20  | ns    |
| t <sub>PLZ</sub>                      | Disable Time Low to Z                                    |                                                                             | 0.3 | 5   | 20  | ns    |
| t <sub>PZH</sub>                      | Enable Time Z to High                                    |                                                                             | 0.3 | 10  | 30  | ns    |
| t <sub>PZL</sub>                      | Enable Time Z to Low                                     |                                                                             | 0.3 | 10  | 30  | ns    |
| DIFFERENTIAL RECEIVER CHARACTERISTICS |                                                          |                                                                             |     |     |     |       |
| t <sub>PHLD</sub>                     | Differential Propagation Delay High to Low               | C <sub>L</sub> = 10 pF, V <sub>ID</sub> = 200 mV<br>(Figure 7 and Figure 8) | 1.5 | 5   | 9   | ns    |
| t <sub>PLHD</sub>                     | Differential Propagation Delay Low to High               |                                                                             | 1.5 | 4.6 | 9   | ns    |
| t <sub>SKD</sub>                      | Differential Skew  t <sub>PHLD</sub> – t <sub>PLHD</sub> |                                                                             | 0   | 0.4 | 3   | ns    |
| t <sub>r</sub>                        | Rise Time                                                |                                                                             | 0   | 1.5 | 5   | ns    |
| t <sub>f</sub>                        | Fall Time                                                |                                                                             | 0   | 1.5 | 5   | ns    |
| t <sub>PHZ</sub>                      | Disable Time High to Z                                   | C <sub>L</sub> = 10 pF<br>(Figure 9 and Figure 10)                          | 1   | 5   | 20  | ns    |
| t <sub>PLZ</sub>                      | Disable Time Low to Z                                    |                                                                             | 1   | 5   | 20  | ns    |
| t <sub>PZH</sub>                      | Enable Time Z to High                                    |                                                                             | 0.3 | 10  | 30  | ns    |
| t <sub>PZL</sub>                      | Enable Time Z to Low                                     |                                                                             | 0.3 | 10  | 30  | ns    |

(1)  $C_L$  includes probe and fixture capacitance.

(2) Generator waveform for all tests unless otherwise specified:  $f = 1\text{ MHz}$ ,  $Z_O = 50\Omega$ ,  $t_r \leq 1\text{ ns}$ ,  $t_f \leq 1\text{ ns}$  (0%–100%).

## PARAMETER MEASUREMENT INFORMATION




Figure 2. Differential Driver DC Test Circuit




Figure 3. Differential Driver Propagation Delay and Transition Time Test Circuit




Figure 4. Differential Driver Propagation Delay and Transition Time Waveforms




Figure 5. Driver TRI-STATE Delay Test Circuit




Figure 6. Driver TRI-STATE Delay Waveforms




Figure 7. Receiver Propagation Delay and Transition Time Test Circuit




Figure 8. Receiver Propagation Delay and Transition Time Waveforms




Figure 9. Receiver TRI-STATE Delay Test Circuit




Figure 10. Receiver TRI-STATE Delay Waveforms

## APPLICATION INFORMATION

### TRUTH TABLES

The DS36C200 has two enable pins DE and RE\*, however, the driver and receiver should never be enabled simultaneously. Enabling both could cause multiple channel contention between the receiver output and the driving logic. It is recommended to route the enables together on the PC board. This will allow a single bit [DE/RE\*] to control the chip. This DE/RE\* bit toggles the DS36C200 between Receive mode and Transmit mode. When the bit is asserted HIGH the device is in Transmit mode. When the bit is asserted LOW the device is in Receive mode. The mode determines the function of the I/O pins: DI/RO, DO/RI+, and DO/RI-. Please note that some of the pins have been identified by its function in the corresponding mode in the three tables below. For example, in Transmit mode the DO/RI+ pin is identified as DO+. This was done for clarity in the tables only and should not be confused with the pin identification throughout the rest of this document. Also note that a logic low on the DE/RE\* bit corresponds to a logic low on both the DE pin and the RE\* pin. Similarly, a logic high on the DE/RE\* bit corresponds to a logic high on both the DE pin and the RE\* pin.

**Table 1. Receive Mode<sup>(1)</sup>**

| Input(s) |     | Input/Output         |    |
|----------|-----|----------------------|----|
| DE       | RE* | [RI+] – [RI-]        | RO |
| L        | L   | > +100 mV            | H  |
| L        | L   | < -100 mV            | L  |
| L        | L   | 100 mV > & > -100 mV | X  |
| L        | H   | X                    | Z  |

- (1) H = Logic high level  
 L = Logic low level  
 X = Indeterminate state  
 Z = High impedance state

**Table 2. Transmit Mode<sup>(1)</sup>**

| Input(s) |     | Input/Output |     |     |
|----------|-----|--------------|-----|-----|
| DE       | RE* | DI           | DO+ | DO- |
| H        | H   | L            | L   | H   |
| H        | H   | H            | H   | L   |
| H        | H   | 2 > & > 0.8  | X   | X   |
| L        | H   | X            | Z   | Z   |

- (1) H = Logic high level  
 L = Logic low level  
 X = Indeterminate state  
 Z = High impedance state

### DEVICE PIN DESCRIPTIONS

| Pin#        | Name            | Mode         | Description                                                                                          |
|-------------|-----------------|--------------|------------------------------------------------------------------------------------------------------|
|             | (In mode only)  |              |                                                                                                      |
| 3           | DE              | Transmit     | Driver Enable: When asserted low driver is disabled. And when asserted high driver is enabled.       |
| 1, 7        | DI              |              | TTL/CMOS driver input pins                                                                           |
| 10, 13      | DO+             |              | Non-inverting driver output pin                                                                      |
| 11, 12      | DO–             |              | Inverting driver output pin                                                                          |
| 4           | RE*             | Receive      | Receiver Enable: When asserted low receiver is enabled. And when asserted high receiver is disabled. |
| 1, 7        | RO              |              | Receiver output pin                                                                                  |
| 10, 13      | RI+             |              | Positive receiver input pin                                                                          |
| 11, 12      | RI–             |              | Negative receiver input pin                                                                          |
| 5           | GND             | Transmit and | Ground pin                                                                                           |
| 2           | V <sub>CC</sub> | Receive      | Positive power supply pin, +5V ± 10%                                                                 |
| 6, 8, 9, 14 | NC              |              | No Connect                                                                                           |

### IEEE 1394

The DS36C200 drives and receives IEEE 1394 physical layer signal levels. The current mode driver is capable of driving a 55Ω load with V<sub>OD</sub> between 172 mV and 285 mV. The DS36C200 is not designed to work with a link layer controller IC requiring full 1394 physical layer compliance to the standard. No clock generator, no arbitration, and no encode/decode logic is provided with this device. For a 1394 link where speed sensing, bus arbitration, and other functions are not required, a controller and the DS36C200 will provide a cost effective, high speed dedicated link. This is shown in [Figure 11](#). In applications that require fully compliant 1394 protocol, a link layer controller and physical layer controller will be required as shown in [Figure 11](#). The physical layer controller supports up to three DS36C200 devices (not shown).

The DS36C200 drivers are current mode drivers and intended to work with a two 110Ω termination resistors in parallel with each other. The termination resistors should match the characteristic impedance of the transmission media. The drivers are current mode devices therefore the resistors are required. Both resistors are required for half duplex operation and should be placed as close to the DO/RI+ and DO/RI– pins as possible at opposite ends of the bus. However, if your application only requires simplex operation, only one termination resistor is required. In addition, note the voltage levels will vary from those in the datasheet due to different loading. Also, AC or unterminated configurations are not used with this device. Multiple node configurations are possible as long as transmission line effects are taken into account. Discontinuities are caused by mid-bus stubs, connectors, and devices that affect signal integrity.

The differential line driver is a balanced current source design. A current mode driver, generally speaking has a high output impedance and supplies a constant current for a range of loads (a voltage mode driver on the other hand supplies a constant voltage for a range of loads). Current is switched through the load in one direction to produce a logic state and in the other direction to produce the other logic state. The typical output current is mere 3.8 mA, a minimum of 3.1 mA, and a maximum of 5.2 mA. The current mode **requires** that a resistive termination be employed to terminate the signal and to complete the loop as shown in [Figure 12](#). The 3.8 mA loop current will develop a differential voltage of 210 mV across the 55Ω termination resistor which the receiver detects with a 110 mV minimum differential noise margin neglecting resistive line losses (driven signal minus receiver threshold (210 mV – 100 mV = 110 mV)). The signal is centered around +1.2V (Driver Offset, V<sub>OS</sub>) with respect to ground as shown in [Figure 8](#).

The current mode driver provides substantial benefits over voltage mode drivers, such as an RS-422 driver. Its quiescent current remains relatively flat versus switching frequency. Whereas the RS-422 voltage mode driver increases exponentially in most case between 20 MHz–50 MHz. This is due to the overlap current that flows between the rails of the device when the internal gates switch. Whereas the current mode driver switches a fixed current between its output without any substantial overlap current. This is similar to some ECL and PECL devices, but without the heavy static I<sub>CC</sub> requirements of the ECL/PECL designs. LVDS requires > 80% less current than similar PECL devices. AC specifications for the driver are a tenfold improvement over other existing RS-422 drivers.

### Fail-safe Feature:


The LVDS receiver is a high gain, high speed device that amplifies a small differential signal (20mV) to CMOS logic levels. Due to the high gain and tight threshold of the receiver, care should be taken to prevent noise from appearing as a valid signal.

The receiver's internal fail-safe circuitry is designed to source/sink a small amount of current, providing fail-safe protection (a stable known state of HIGH output voltage) for floating, terminated or shorted receiver inputs.

1. **Open Input Pins.** The DS36C200 is a dual transceiver device, and if an application requires only one receiver, the unused channel inputs should be left OPEN. Do not tie the receiver inputs to ground or any other voltages. The input is biased by internal high value pull up or pull down resistors to set the output to a HIGH state. This internal circuitry will ensure a HIGH, stable output state for open inputs.
2. **Terminated Input.** If the driver is disconnected (cable unplugged), or if the driver is in a TRI-STATE or power-off condition, the receiver output will again be in a HIGH state, even with the end of the cable 100Ω termination resistor across the input pins. The unplugged cable can become a floating antenna which can pick up noise. If the cable picks up more than 10mV of differential noise, the receiver may see the noise as a valid signal and switch. To insure that any noise is seen as common-mode and not differential, a balanced interconnect should be used. Twisted pair cable will offer better balance than flat ribbon cable.
3. **Shorted Inputs.** If a fault condition occurs that shorts the receiver inputs together, thus resulting in a 0V differential input voltage, the receiver output will remain in a HIGH state. Shorted input fail-safe is not supported across the common-mode range of the device (GND to 2.4V). It is only supported with inputs shorted and no external common-mode voltage applied.

If there is more than 10mV of differential noise, the receiver may switch or oscillate. If this condition can happen in your application, you may wish to add external fail-safe resistors to create a larger noise margin. External lower value pull up and pull down resistors (for a stronger bias) may be used to boost fail-safe in the presence of higher noise levels. The pull up and pull down resistors should be in the 5kΩ to 15kΩ range to minimize loading and waveform distortion to the driver. The common-mode bias point should be set to approximately 1.2V (less than 1.75V) to be compatible with the internal circuitry.

Additional information on fail-safe biasing of LVDS devices may be found in AN-1194 ([SNLA051](#)).



**Figure 11. (A) Dedicated IEEE 1394 Link  
(B) Full IEEE 1394 Compliant Link**





Figure 12. Typical in Home Application

Figure 13. Typical Interface Connection <sup>(1)</sup>

- (1) The DS36C200 is a current mode device and only function with datasheet specification when a resistive load is applied to the drivers outputs.

## REVISION HISTORY

### Changes from Revision C (April 2013) to Revision D

### Page

- Changed layout of National Data Sheet to TI format ..... [10](#)

## PACKAGING INFORMATION

| Orderable part number           | Status<br>(1) | Material type<br>(2) | Package   Pins | Package qty   Carrier | RoHS<br>(3) | Lead finish/<br>Ball material<br>(4) | MSL rating/<br>Peak reflow<br>(5) | Op temp (°C) | Part marking<br>(6) |
|---------------------------------|---------------|----------------------|----------------|-----------------------|-------------|--------------------------------------|-----------------------------------|--------------|---------------------|
| <a href="#">DS36C200M/NOPB</a>  | Active        | Production           | SOIC (D)   14  | 55   TUBE             | Yes         | SN                                   | Level-1-260C-UNLIM                | 0 to 70      | DS36C200M           |
| DS36C200M/NOPB.A                | Active        | Production           | SOIC (D)   14  | 55   TUBE             | Yes         | SN                                   | Level-1-260C-UNLIM                | 0 to 70      | DS36C200M           |
| <a href="#">DS36C200MX/NOPB</a> | Active        | Production           | SOIC (D)   14  | 2500   LARGE T&R      | Yes         | SN                                   | Level-1-260C-UNLIM                | 0 to 70      | DS36C200M           |
| DS36C200MX/NOPB.A               | Active        | Production           | SOIC (D)   14  | 2500   LARGE T&R      | Yes         | SN                                   | Level-1-260C-UNLIM                | 0 to 70      | DS36C200M           |

<sup>(1)</sup> **Status:** For more details on status, see our [product life cycle](#).

<sup>(2)</sup> **Material type:** When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

<sup>(3)</sup> **RoHS values:** Yes, No, RoHS Exempt. See the [TI RoHS Statement](#) for additional information and value definition.

<sup>(4)</sup> **Lead finish/Ball material:** Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

<sup>(5)</sup> **MSL rating/Peak reflow:** The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.


<sup>(6)</sup> **Part marking:** There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

**Important Information and Disclaimer:** The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.


## TAPE AND REEL INFORMATION



\*All dimensions are nominal

| Device          | Package Type | Package Drawing | Pins | SPQ  | Reel Diameter (mm) | Reel Width W1 (mm) | A0 (mm) | B0 (mm) | K0 (mm) | P1 (mm) | W (mm) | Pin1 Quadrant |
|-----------------|--------------|-----------------|------|------|--------------------|--------------------|---------|---------|---------|---------|--------|---------------|
| DS36C200MX/NOPB | SOIC         | D               | 14   | 2500 | 330.0              | 16.4               | 6.5     | 9.35    | 2.3     | 8.0     | 16.0   | Q1            |


## TAPE AND REEL BOX DIMENSIONS



\*All dimensions are nominal


| Device          | Package Type | Package Drawing | Pins | SPQ  | Length (mm) | Width (mm) | Height (mm) |
|-----------------|--------------|-----------------|------|------|-------------|------------|-------------|
| DS36C200MX/NOPB | SOIC         | D               | 14   | 2500 | 367.0       | 367.0      | 35.0        |

## TUBE




\*All dimensions are nominal

| Device           | Package Name | Package Type | Pins | SPQ | L (mm) | W (mm) | T (μm) | B (mm) |
|------------------|--------------|--------------|------|-----|--------|--------|--------|--------|
| DS36C200M/NOPB   | D            | SOIC         | 14   | 55  | 495    | 8      | 4064   | 3.05   |
| DS36C200M/NOPB.A | D            | SOIC         | 14   | 55  | 495    | 8      | 4064   | 3.05   |

**D0014A****PACKAGE OUTLINE****SOIC - 1.75 mm max height**

SMALL OUTLINE INTEGRATED CIRCUIT



4220718/A 09/2016

**NOTES:**

1. All linear dimensions are in millimeters. Dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. This dimension does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.15 mm, per side.
4. This dimension does not include interlead flash. Interlead flash shall not exceed 0.43 mm, per side.
5. Reference JEDEC registration MS-012, variation AB.




**TEXAS  
INSTRUMENTS**  
www.ti.com

# EXAMPLE BOARD LAYOUT



D0014A

SOIC - 1.75 mm max height

SMALL OUTLINE INTEGRATED CIRCUIT



LAND PATTERN EXAMPLE  
SCALE:8X



SOLDER MASK DETAILS

4220718/A 09/2016

NOTES: (continued)

6. Publication IPC-7351 may have alternate designs.


7. Solder mask tolerances between and around signal pads can vary based on board fabrication site.

## EXAMPLE STENCIL DESIGN

D0014A

SOIC - 1.75 mm max height

SMALL OUTLINE INTEGRATED CIRCUIT



SOLDER PASTE EXAMPLE  
BASED ON 0.125 mm THICK STENCIL  
SCALE:8X

4220718/A 09/2016

NOTES: (continued)

8. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release. IPC-7525 may have alternate design recommendations.
9. Board assembly site may have different recommendations for stencil design.

## IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATA SHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, regulatory or other requirements.

These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to [TI's Terms of Sale](#) or other applicable terms available either on [ti.com](https://www.ti.com) or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

TI objects to and rejects any additional or different terms you may have proposed.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2025, Texas Instruments Incorporated